Pioneer sound.vision.soul

Service Manual

DV-667A-K

ORDER NO.
RRV2808

DVD PLAYER

DV-667A-K
DV-667A-S

THIS MANUAL IS APPLICABLE TO THE FOLLOWING MODEL(S) AND TYPE(S).

Model	Type	Power Requirement	Region No.	**Serial No.** Confirm 3rd & 4th alphabetical letters.
DV-667A-K	RDXU/RA	AC110-127V/220-240V	1	&&PG######$$
DV-667A-K	RPWXU	AC110-127V/220-240V	4	&&PG######$$
DV-667A-S	RLXJ/NC	AC110-127V/220-240V	3	&&MP######$$
DV-667A-S	BKXJ	AC110V/220V	3	&&MP######$$
DV-667A-S	LFXJ	AC110V	3	&&MP######$$
DV-667A-S	RTXJN	AC110-127V/220-240V	3	&&TM######$$



PIONEER CORPORATION 4-1, Meguro 1-chome, Meguro-ku, Tokyo 153-8654, Japan
PIONEER ELECTRONICS (USA) INC. P.O. Box 1760, Long Beach, CA 90801-1760, U.S.A.
PIONEER EUROPE NV Haven 1087, Keetberglaan 1, 9120 Melsele, Belgium
PIONEER ELECTRONICS ASIACENTRE PTE. LTD. 253 Alexandra Road, #04-01, Singapore 159936

T-ZZE JULY 2003 printed in Japan

SAFETY INFORMATION

This service manual is intended for qualified service technicians ; it is not meant for the casual do-it-yourselfer. Qualified technicians have the necessary test equipment and tools, and have been trainedto properly and safely repair complex products such as those covered by this manual.Improperly performed repairs can adversely affect the safety and reliability of the product and mayvoid the warranty. If you are not qualified to perform the repair of this product properly and safely, youshould not risk trying to do so and refer the repair to a qualified service technician.

WARNING !

THE AEL (ACCESSIBLE EMISSION LEVEL) OF THE LASER POWER OUTPUT IS LESS THAN CLASS 1 BUT THE LASER COMPONENT IS CAPABLE OF EMITTING RADIATION EXCEEDING THE LIMIT FOR CLASS 1.
A SPECIALLY INSTRUCTED PERSON SHOULD DO SERVICING OPERATION OF THE APPARATUS.

LASER DIODE CHARACTERISTICS

FOR DVD :	MAXIMUM OUTPUT POWER : 5 mW WAVELENGTH : 650 nm
FOR CD :	MAXIMUM OUTPUT POWER : 5 mW WAVELENGTH : 780 nm

LABEL CHECK

[RD/RA, RPW, RL/NC and RT types]

CAUTION	: VISIBLE AND INVISIBLE LASER RADIATION WHEN OPEN. AVOID EXPOSURE TO BEAM.
VORSICHT	: SICHTBARE UND UNSICHTBARE LASERSTRAHLUNG, WENNABDECKUNG GEÖFFNET NICHT DEM STRAHL AUSSETZEN!
ADVARSEL	: SYNLIG OG USYNLIG LASERSTRÅLING VED ÅBNING UNDGÅ UDSÆTTELSE FOR STRÅLING.
VARNING	: SYNLIG OCH OSYNLIG LASERSTRÅLNING NÄR DENNA DEL ÄR ÖPPNAD BETRAKTA EJ STRÅLEN.
VARO!	: AVATTAESSA ALTISTUT NÄKYVÄ JA NÄKYMÄTTÖMÄLLE LASERSATEIL YLLE. ÄLÄ KATSO SÄTEESEN.
CUIDADO	: RADIACIÓN LÁSER VISIBLE E INVISIBLE AL ESTAR ABIERTO. EVITAR EXPOSICIÓN AL RAYO.

VRW1872

[BK type]

CAUTION	: VISIBLE AND INVISIBLE LASER RADIATION WHEN OPEN. AVOID EXPOSURE TO BEAM.
VORSICHT	: SICHTBARE UND UNSICHTBARE LASERSTRAHLUNG, WENNABDECKUNG GEÖFFNET NICHT DEM STRAHL AUSSETZEN!
ADVARSEL	: SYNLIG OG USYNLIG LASERSTRÅLING VED ÅBNING UNDGÅ UDSÆTTELSE FOR STRÅLING.
VARNING	: SYNLIG OCH OSYNLIG LASERSTRÅLNING NÄR DENNA DEL ÄR ÖPPNAD BETRAKTA EJ STRÅLEN.
VARO!	: AVATTAESSA ALTISTUT NÄKYVÄ JA NÄKYMÄTTÖMÄLLE LASERSATEIL YLLE. ÄLÄ KATSO SÄTEESEN.
주의	: 뚜껑을 열게 되면, 시각적으로 보이지 않는 레이저 광선과 보이는 광선이 방출되므로 광선의 방출에 쏘이지 않도록 주의할 것.

VRW1886

[LF type]

CAUTION : VISIBLE AND INVISIBLE LASER RADIATION WHEN OPEN. AVOID EXPOSURE TO BEAM.

注意 : 若打開會發生可見和不可見的鐳射輻射，請勿受輻射。

VRW1961

(Printed on the Rear Panel)

[RPW, RL/NC, LF and RT types]

CLASS 1
LASER PRODUCT



Additional Laser Caution

1. Laser Interlock Mechanism
   • Loading switch (S101 on the LOAB Assy) is used for interlock mechanism of the laser.
   When this switch turned ON in SW2 (CLOSE) side (OPEN signal is 0V and CLOSE signal is 3.5V), a laser becomes the status which can completely oscillation.
   Furthermore, the laser completely oscillates in the disc judgment and disc playback.
   When player is power ON state and laser diode is not completely oscillating, 780nm laser diode is always oscillating by half power.
   • Laser diode is driving with Q201 (650nm LD) and Q211 (780nm LD) on the DVDM Assy.
   Therefore, when short-circuit between the emitter and collector of these transistors or the base voltage is supplied for transistors turn on, the laser oscillates. (failure mode)
   • In the test mode ∗ , there is the mode that the laser oscillates except for the disc judgment and playback. LD ON mode in the test mode oscillates with the laser forcibly.
   The interlock mechanism mentioned above becomes invalid in this mode.

2. When the cover is open, close viewing through the objective lens with the naked eye will cause exposure to the laser beam.

∗ : See page 49.

[Important symbols for good services]
In this manual, the symbols shown-below indicate that adjustments, settings or cleaning should be made securely.
When you find the procedures bearing any of the symbols, be sure to fulfill them:

1. Product safety

You should conform to the regulations governing the product (safety, radio and noise, and other regulations), and should keep the safety during servicing by following the safety instructions described in this manual.

2. Adjustments

To keep the original performances of the product, optimum adjustments or specification confirmation is indispensable. In accordance with the procedures or instructions described in this manual, adjustments should be performed.

3. Cleaning

For optical pickups, tape-deck heads, lenses and mirrors used in projection monitors, and other parts requiring cleaning, proper cleaning should be performed to restore their performances.

4. Shipping mode and shipping screws

To protect the product from damages or failures that may be caused during transit, the shipping mode should be set or the shipping screws should be installed before shipping out in accordance with this manual, if necessary.

5. Lubricants, glues, and replacement parts

Appropriately applying grease or glue can maintain the product performances. But improper lubrication or applying glue may lead to failures or troubles in the product. By following the instructions in this manual, be sure to apply the prescribed grease or glue to proper portions by the appropriate amount.For replacement parts or tools, the prescribed ones should be used.

CONTENTS

1. SPECIFICATIONS

General

System . . . . . .DVD player
Power requirements
LF type . . . . . AC 110 V, 60 Hz
BK type . . . . . AC 110/220V, 60 Hz
Other types. . . . . AC 110–127/220–240 V, 50/60 Hz
Power consumption
. . . . . 14 W
Power consumption (standby)
LF type. . . . . 0.1 W
Other types . . . . . 0.18 W
Weight . . . . . 2.4 kg / 5 lb 3 oz
Dimensions . . 420 (W) x 55 (H) x 283 (D) mm
(16.5 (W) x 2.2 (H) x 11.1 (D) in.)
Operating temperature . . . . . .+5°C to +35°C
(+41°F to +95°F)
Operating humidity . . . . . 5% to 85%
(no condensation)

Component video output

Y (luminance) - Output level . . . . . 1 Vp-p (75 Ω)
P_B (color) - Output level . . . . . 0.7 Vp-p (75 Ω)
P_R (color) - Output level . . . . . 0.7 Vp-p (75 Ω)
Jack . . . . . RCA jacks

D1/D2 Video output *(LF type only)*

Output level . . . . . Y: 1.0 Vp-p (75Ω)
P_B, P_R: 0.7 Vp-p (75Ω)
Jack . . . . . D terminal

S-video output

Y (luminance) - Output level . . . . . 1 Vp-p (75 Ω)
C (color) - Output level. . . . . 286 mVp-p (75 Ω)
Jack . . . . . S-video jack

Video output

Output level . . . . . 1 Vp-p (75 Ω)
Jack. . . . . RCA jack

Audio output (1 stereo pair)

Output level . . . . . During audio output
200 mVrms (1 kHz, –20 dB)
Number of channels 2
Jacks . . . . . RCA jack

Audio output (multi-channel / L, R, C, SW, LS, RS)

Output level . . . . . During audio output
200 mVrms (1 kHz, –20 dB)
Number of channels 6
Jacks . . . . . RCA jack

Digital audio characteristics

Frequency response
. . . . . 4 Hz to 44 kHz (DVD fs: 96 kHz)
. . . . . 4 Hz to 88 kHz (DVD-Audio fs: 192 kHz)
S/N ratio . . . . . 118 dB
Dynamic range . . . . . 108 dB
Total harmonic distortion . . . . . 0.0014 %
Wow and flutter . . . . . Limit of measurement
(±0.001% W. PEAK) or lower

Digital output

Optical digital output . . . . . Optical digital jack
Coaxial digital output . . . . . RCA jack

Other terminals

Control in . . . . . Minijack (3.5 ø)
Control out . . . . . Minijack (3.5 ø)

Accessories

Audio/video cable 1
Power cable 1
Remote control 1
AA/R6P dry cell batteries 2
Operating Instructions
. . . . . 1 (RD/RA, RPW, BK and RT types)
. . . . . 2 (RL/NC and LF types)
Warranty card (RD/RA type only). 1
Front panel button names sticker
(LF type only) 1
Remote control overlay
(LF type only) 1

Note

- The specifications and design of this product are subject to change without notice, due to improvement.

2. EXPLODED VIEWS AND PARTS LIST

NOTES:
- *Parts marked by "NSP" are generally unavailable because they are not in our Master Spare Parts List.*
- *The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.*
- *Screws adjacent to ▼ mark on product are used for disassembly.*
- *For the applying amount of lubricants or glue, follow the instructions in this manual. (In the case of no amount instructions, apply as you think it appropriate.)*

2.1 PACKING



PACKING parts List

Mark	No.	Description	Part No.
⚠	1	Power Cable	See Contrast table (2)
	2	• • • • •	
	3	Audio / Video Cable	See Contrast table (2)
	4	Remote Control	VXX2865
	5	Battery Cover	VNK4997
NSP	6	AA/R6P Dry Cell Batteries	See Contrast table (2)
	7	Operating Instructions (English)	See Contrast table (2)
	8	• • • • •	
	9	Operating Instructions (Trad-Chinese)	See Contrast table (2)
	10	Operating Instructions (Thai)	See Contrast table (2)
	11	Operating Instructions (Korean)	See Contrast table (2)
NSP	12	Warranty Card	See Contrast table (2)
	13	Polyethylene Bag	VHL1051
	14	Sheet	Z23-007
	15	Pad L	See Contrast table (2)
	16	Pad R	See Contrast table (2)
	17	Packing Case	See Contrast table (2)
	18	Accessory Box	See Contrast table (2)
	19	Paper Board	See Contrast table (2)
	20	Remote Control Overlay	See Contrast table (2)
NSP	21	Front Panel Botton Names Sticker	See Contrast table (2)

(2) CONTRAST TABLE

DV-667A-K/RDXU/RA, RPWXU, DV-667A-S/RLXJ/NC, BKXJ, LFXJ and RTXJN are constructed the same except for the following :

Mark	No.	Symbol and Description	DV-667A-K/ RDXU/RA	DV-667A-K/ RPWXU	DV-667A-S/ RLXJ/NC	DV-667A-S/BKXJ	DV-667A-S/LFXJ	DV-667A-S/ RTXJN
⚠	1	Power Cable	ADG7003	ADG1124	ADG1154	DDG1086	ADG1158	ADG1154
	3	Audio / Video Cable	VDE1077	VDE1077	XDE3049	XDE3049	XDE3049	XDE3049
NSP	6	AA/R6P Dry Cell Batteries	VEM1030	VEM1030	VEM1031	VEM1031	VEM1031	VEM1031
	7	Operating Instructions (English)	VRB1311	VRB1311	VRB1311	Not used	VRB1311	Not used
	9	Operating Instructions (Trad-Chinese)	Not used	Not used	VRC1179	Not used	VRC1179	Not used
	10	Operating Instructions (Thai)	Not used	Not used	Not used	Not used	Not used	VRC1181
	11	Operating Instructions (Korean)	Not used	Not used	Not used	VRC1180	Not used	Not used
NSP	12	Warranty Card	ARY7025	Not used	Not used	Not used	Not used	Not used
	15	Pad L	VHA1319	VHA1319	VHA1323	VHA1323	VHA1323	VHA1342
	16	Pad R	VHA1320	VHA1320	VHA1324	VHA1324	VHA1324	VHA1343
	17	Packing Case	VHG2340	VHG2341	VHG2386	VHG2384	VHG2339	VHG2387
	18	Accessory Box	Not used	VHC1102	Not used	Not used	Not used	Not used
	19	Paper Board	VHC1100	Not used	VHC1105	VHC1105	VHC1105	VHC1109
	20	Remote Control Overlay	Not used	Not used	Not used	Not used	VEC2341	Not used
NSP	21	Front Panel Botton Names Sticker	Not used	Not used	Not used	Not used	VRW1957	Not used

2.2 EXTERIOR SECTION



EXTERIOR SECTION parts List

Mark	No.	Description	Part No.
	1	DVDM Assy	VWS1563
	2	JCKB Assy	See Contrast table (2)
	3	• • • • •	
⚠	4	POWER SUPPLY Unit	VWR1366
NSP	5	Loading Mecha. Assy	VWT1207
	6	Connector Assy	PG05KK-E37
	7	Flexible Cable (33P)	See Contrast table (2)
	8	Connector Assy (13P)	PF13PP-D27
	9	• • • • •	
	10	Cord Clamper	RNH-184
	11	Rubber Foot	VEB1349
	12	PCB Support	VEC2184
	13	Cushion	VEC2342
	14	Rear Panel	See Contrast table (2)
NSP	15	Base Chassis	See Contrast table (2)
	16	PCB Base	See Contrast table (2)
	17	PCB Base	See Contrast table (2)
NSP	18	S Earth Plate	VNF1128
	19	Adapter 3L	See Contrast table (2)
	20	Adapter 3R	See Contrast table (2)
	21	Bonnet Case S	See Contrast table (2)
	22	Tray Panel	See Contrast table (2)
	23	Acryl Door	See Contrast table (2)
	24	KUC Label	See Contrast table (2)
	25	Screw	BBZ30P060FMC
	26	Screw	BBZ30P080FZK
	27	Screw	See Contrast table (2)
	28	Screw	PPZ30P080FMC
	29	• • • • •	
	30	Hologram Sheet	VEC2359
	31	Caution Label	See Contrast table (2)

(2) CONTRAST TABLE

DV-667A-K/RDXU/RA, RPWXU, DV-667A-S/RLXJ/NC, BKXJ, LFXJ and RTXJN are constructed the same except for the following :

Mark	No.	Symbol and Description	DV-667A-K/ RDXU/RA	DV-667A-K/ RPWXU	DV-667A-S/ RLXJ/NC	DV-667A-S/BKXJ	DV-667A-S/LFXJ	DV-667A-S/ RTXJN
	2	JCKB Assy	VWV1942	VWV1942	VWV1942	VWV1942	VWV1946	VWV1942
	7	Flexible Cable (33P)	VDA1956	VDA1956	VDA1955	VDA1955	VDA1955	VDA1955
	14	Rear Panel	VNA2576	VNA2582	VNA2604	VNA2602	VNA2581	VNA2633
NSP	15	Base Chassis	VNA2614	VNA2614	VNA2584	VNA2584	VNA2584	VNA2605
	16	PCB Base	VNE2278	VNE2278	VNE2277	VNE2277	VNE2277	VNE2277
	17	PCB Base	VNE2310	VNE2310	VNE2312	VNE2312	VNE2312	VNE2312
	19	Adapter 3L	VNL1960	VNL1960	VNL1958	VNL1958	VNL1958	VNL1958
	20	Adapter 3R	VNL1961	VNL1961	VNL1959	VNL1959	VNL1959	VNL1959
	21	Bonnet Case S	VXX2873	VXX2873	VXX2878	VXX2878	VXX2878	VXX2878
	22	Tray Panel	VNK5281	VNK5281	VNK5367	VNK5367	VNK5367	VNK5367
	23	Acryl Door	VEC2334	VEC2334	VEC2340	VEC2340	VEC2340	VEC2340
	24	KUC Label	VRW1959	VRW1959	VRW1959	Not used	Not used	VRW1959
	24	KOR Label	Not used	Not used	Not used	VRW1970	Not used	Not used
	24	TWN Label	Not used	Not used	Not used	Not used	VRW1969	Not used
	27	Screw	BCZ40P060FZK	BCZ40P060FZK	BCZ40P060FNI	BCZ40P060FNI	BCZ40P060FNI	BCZ40P060FNI
	31	Caution Label	VRW1872	VRW1872	VRW1872	VRW1886	VRW1961	VRW1872

2.3 FRONT PANEL SECTION



FRONT PANEL SECTION parts List

Mark	No.	Description	Part No.
	1	FLKY Assy	See Contrast table (2)
NSP	2	PWSB Assy	VWG2429
	3	Connector Assy	PF03PP-B07
	4	Flexible Cable (21P)	See Contrast table (2)
	5	Rubber Foot	VEB1349
	6	FL Lens	See Contrast table (2)
	7	FL Filter	See Contrast table (2)
	8	• • • • •	
	9	FP Angle	See Contrast table (2)
	10	Front Panel Assy	See Contrast table (2)
	11	Pioneer Name Plate	See Contrast table (2)
	12	Screw	PPZ30P080FMC

(2) CONTRAST TABLE

DV-667A-K/RDXU/RA, RPWXU, DV-667A-S/RLXJ/NC, BKXJ, LFXJ and RTXJN are constructed the same except for the following :

Mark	No.	Symbol and Description	DV-667A-K/ RDXU/RA	DV-667A-K/ RPWXU	DV-667A-S/ RLXJ/NC	DV-667A-S/BKXJ	DV-667A-S/LFXJ	DV-667A-S/ RTXJN
	1	FLKY Assy	VWG2436	VWG2436	VWG2436	VWG2436	VWG2437	VWG2436
	4	Flexible Cable (21P)	VDA1957	VDA1957	VDA1968	VDA1968	VDA1968	VDA1968
	6	FL Lens	VEC2336	VEC2336	VEC2357	VEC2357	VEC2357	VEC2357
	7	FL Filter	VEC2339	VEC2339	VEC2344	VEC2344	VEC2344	VEC2344
	9	FP Angle	VNE2300	VNE2300	VNE2304	VNE2304	VNE2304	VNE2304
	10	Front Panel Assy	VXA2584	VXA2584	VXA2583	VXA2583	VXA2583	VXA2610
	11	Pioneer Name Plate	VAM1130	VAM1130	VAM1129	VAM1129	VAM1129	VAM1129

2.4 LOADING MECHA ASSY

Note :

Refer to
" ■ Application of Lubricant".



LOADING MECHA ASSY parts List

Mark	No.	Description	Part No.
NSP	1	LOAB Assy	VWG2426
	2	Traverse Mecha. Assy-S	VXX2871
	3	Loading Motor Assy	VXX2872
	4	Motor Pulley	PNW1634
	5	Motor	VXM1105
	6	Flexible Cable (24P)	VDA1945
	7	Connector Assy 2P	VKP2253
	8	Floating Rubber	VEB1351
	9	Belt	VEB1330
	10	Stabilizer	VNE2253
	11	Loading Base	VNL1917
	12	Float Base DVD	VNL1918
	13	Drive Cam	VNL1919
	14	Gear Pulley	VNL1921
	15	Loading Gear	VNL1922
	16	Drive Gear	VNL1923
	17	SW Lever	VNL1925
	18	Clamper Plate	VNE2251
	19	Bridge	VNE2252
	20	Clamper	VNL1924
	21	Screw	JGZ17P028FMC
	22	Screw	Z39-019
	23	Tray	VNL1920

Application of Lubricant





● Front View



● Rear View



● Top View



● Bottom View

2.5 TRAVERSE MECHA ASSY-S



TRAVERSE MECHA ASSY-S parts List

Mark	No.	Description	Part No.
	1	Spindle Motor	VXM1099
	2	Stepping Motor	VXM1101
	3	Pickup Assy-S	OXX8005
	4	Skew Screw	VBA1080
	5	Skew Spring	VBH1335
	6	Guide Bar	VLL1514
	7	Sub Guide Bar	VLL1515
	8	Leaf Spring	VNC1023
	9	Joint Spring	VNC1019
	10	Support Spring	VNC1020
NSP	11	Mecha.Chassis	VNE2248
	12	Damper Sheet	VEB1335
	13	Spacer	VNL1913
	14	Joint 03	VNL1949
	15	Tapping Screw	OBA8021
	16	Screw	BBZ20P050FZK
	17	Screw	PMA26P100FMC

3. BLOCK DIAGRAM AND SCHEMATIC DIAGRAM

3.1 BLOCK DIAGRAM




C JCKB ASSY
IC201
DSD1791DBR
Audio DAC (L, R)
IC204
BA4560F
Audio LPF & Amp.
IC301
DSD1702EG
Audio DAC (Ls, Rs)
IC302
BA4560F
Audio LPF & Amp.
IC401
DSD1702EG
Audio DAC (C, Lfe)
IC402
BA4560F
Audio LPF & Amp.
IC701
LA73054
Video Amp.
IC101
NJM78M05FA
5V REG.
Q101
REG.
IC771
MM1565AF
5V REG.
DAC L/D0
DAC R
DAC C/D1
DAC LFE
DAC LS/D2
DAC RS
V+3D
V+12A
V+6
A_DOUT
CR/R
Y/G
CB/B
V
C
Y
IR
SEL IR
JA602
IN
OUT
JA601
CONTROL
JA101
FRONT
SURROUND
CENTER
SUB WOOFER
JA801
DIGITAL AUDIO OUT OPTICAL
JA102
(19P)
Q801
DIGITAL AUDIO OUT COAXIAL
AUDIO OUT
COMPONENT VIDEO OUT
VIDEO OUT
S VIDEO OUT
CN701
(14P)
D-CONNECTOR
LFXJ type only

3.2 LOAB ASSY and OVERALL WIRING DIAGRAM

Note : When ordering service parts, be sure to refer to "EXPLODED VIEWS and PARTS LIST" or "PCB PARTS LIST".




RF : RF SIGNAL ROUTE
(F) : FOCUS SERVO LOOP LINE
(T) : TRACKING SERVO LOOP LINE
(S) : STEPPING SERVO LOOP LINE
D FLKY ASSY
(LFXJ type: VWG2437)
(Other types: VWG2436)
E PWSB ASSY
(VWG2429)
PICKUP ASSY-S
(OXX8005)
B DVDM ASSY
(VWS1563)
STEPPING MOTOR
: VXM1101
SPINDLE
MOTOR
: VXM1099
A LOAB ASSY
(VWG2426)
LOADING
MOTOR ASSY
: VXX2872
F
POWER SUPPLY UNIT
(VWR1366)
NEUTRAL
LIVE
⚠の部品は、指定部品（安全規格適合部品）を必ず使用すること。
Part marked Triangle Sign shall be replaced with the same part.
(safety regulation authorized)

3.3 DVDM ASSY 1/3 [FRONT END BLOCK]



RF ➡ : RF SIGNAL ROUTE
➡ : FE_DATA SIGNAL ROUTE
F ◣ : FOCUS SERVO LOOP LINE
T ◣ : TRACKING SERVO LOOP LINE
S ◣ : STEPPING SERVO LOOP LINE

①– ⑤: Refer to "3.10 WAVEFORMS".



***: parts not mounted

B 1/3

3.4 DVDM ASSY 2/3 [BACK END BLOCK]

B 2/3 DVDM ASSY (VWS1563)




: FE_DATA SIGNAL ROUTE
V : V SIGNAL ROUTE
S-C/C : S-VIDEO OUT C/C SIGNAL ROUTE
S-Y/Y : S-VIDEO OUT Y/Y SIGNAL ROUTE
R/Cr : R/Cr SIGNAL ROUTE
G/Y : G/Y SIGNAL ROUTE
B/Cb : B/Cb SIGNAL ROUTE
AD : AUDIO DATA SIGNAL ROUTE
D : AUDIO(DIGITAL) SIGNAL ROUTE
CN602
CN601
to JACB
C1/2 CN102
C1/2 CN101
IC602 K4S281632D-TC75 128M SDRAM
Serial Bus BUFFER
only SACD model
STAND BY
Chip Size
RESISTOR
CAPACITOR

B 2/3

3.5 DVDM ASSY 3/3 [SACD and POWER SUPPLY BLOCK]

B 3/3 DVDM ASSY (VWS1563)

AD ⇨ : AUDIO DATA SIGNAL ROUTE

D ⇨ : AUDIO(DIGITAL) SIGNAL ROUTE



: The power supply is shown with the marked box.



B 3/3

3.6 JCKB ASSY 1/2 [AUDIO BLOCK]

C 1/2 JCKB ASSY
(LFXJ type: VWV1946)
(Other types: VWV1942)

: The power supply is shown with the marked box.

V : V SIGNAL ROUTE
S-C/C : S-VIDEO OUT C/C SIGNAL ROUTE
S-Y/Y : S-VIDEO OUT Y/Y SIGNAL ROUTE
R/Cr : R/Cr SIGNAL ROUTE
G/Y : G/Y SIGNAL ROUTE
B/Cb : B/Cb SIGNAL ROUTE
D : AUDIO(DIGITAL) SIGNAL ROUTE
: AUDIO SIGNAL ROUTE



⑥– ⑪: Refer to "3.10 WAVEFORMS".



3.7 JCKB ASSY 2/2 [VIDEO BLOCK]

C 2/2 JCKB ASSY
(LFXJ type: VWV1946)
(Other types: VWV1942)

V ➡ : V SIGNAL ROUTE
S-C/C ➡ : S-VIDEO OUT C/C SIGNAL ROUTE
S-Y/Y ➡ : S-VIDEO OUT Y/Y SIGNAL ROUTE
R/Cr ➡ : R/Cr SIGNAL ROUTE
G/Y ➡ : G/Y SIGNAL ROUTE
B/Cb ➡ : B/Cb SIGNAL ROUTE
D ⇨ : AUDIO(DIGITAL) SIGNAL ROUTE
⇨ : AUDIO SIGNAL ROUTE



: The power supply is shown with the marked box.





C 2/2



MODE	V	Y/C	RGB
VSEL1 (BLANK)	L	L	H
VSEL2	H	L	H

⑫– ⑰: Refer to "3.10 WAVEFORMS".

C 2/2

3.8 FLKY and PWSB ASSYS



S101	O
S102	O
S103	O
S104	O
S105	O
S106	O
S107	O
S108	×
S109	O

S110	O
S111	O
S112	O
S113	O
S114	O
S115	O
S116	O
S117	O
S118	O
S119	×

R151	1.2k
R152	0
R153	2.2k
R154	×
R155	3.9k
R156	2.7k
R158	2.2k
R159	1.2k
R160	0
R161	×

R162	12k
R163	6.8k
R164	3.9k
R165	2.7k
R166	2.2k
R167	1.2k
R168	0
R169	3.9k
R170	2.7k

Note1, Note2, Note3 10k

	LF	Others
R185	O	×
R187	O	O
R189	×	×
R186	×	O
R188	×	×
R190	O	O

R103	×
R105	×
R107	×
R104	O
R106	O
R108	O
R109	×
R110	O
R111	×
R112	O

R184	×
R199	o

: The power supply is shown with the marked box.



KEY0

0	[POWER]
1.2k	[PLAY]
2.2k	[>>]
2.7k	[FL DIM]
3.9k	[<<]

KEY1

0	[PAUSE]
1.2k	[TOP MENU]
2.2k	[LEFT]
2.7k	[ENTER]
3.9k	[DOWN]
6.8k	[MENU]
12k	[UP]

KEY2

0	[EJECT]
1.2k	[STOP]
2.2k	[RIGHT]
2.7k	[GUIDE]
3.9k	[RETURN]

B 3/3
CN105

FLKY ASSY
S102 : FL DIMMER
S103 : I◄◄ ◄◄
S104 : ►► ►►I
S105 : ■
S106 : II
S107 : ►
S109 : ▲
S110 : RETURN
S111 : MENU
S112 : ➡
S113 : ⬆
S114 : TOP MENU
S115 : ENTER
S116 : ⬅
S117 : HOME MENU
S118 : ⬇

PWSB ASSY
S101 : ⏻ STANDBY ON

D E

3.9 POWER SUPPLY UNIT

CAUTION : FOR CONTINUED PROTECTION AGAINST RISK OF FIRE. REPLACE ONLY WITH SAME TYPE NO. 491.800 MFD, BY LITTELFUSE INC. FOR P301 (AEK7063).

CAUTION : FOR CONTINUED PROTECTION AGAINST RISK OF FIRE. REPLACE ONLY WITH SAME TYPE NO. 49101.6 MFD, BY LITTELFUSE INC. FOR P101 (AEK7066).



F POWER SUPPLY UNIT (VWR1366)

≪ **NOTE OF SPARE PARTS IN POWER SUPPLY (SYPS) UNIT** ≫

- In case of repairing, use the described parts only to prevent an accident.
- Please write the red √ mark on the board when the primary section of POWER SUPPLY (SYPS) Unit is repaired.
- Please take care to keep the space, not touching other parts when replacing the parts.

• NOTE FOR FUSE REPLACEMENT

CAUTION -FOR CONTINUED PROTECTION AGAINST RISK OF FIRE. REPLACE WITH SAME TYPE AND RATINGS ONLY.

3.10 WAVEFORMS

Note : The encircled numbers denote measuring point in the schematic diagram.

Measurement condition : No. 1 to 2 and 12 to 17 : reference A1 (DVD), T2-chp 19, Color-bar
No. 6 to 11 : reference A1 (DVD), T2-chp 1

B DVDM ASSY

1 **IC301 - pin 99 [RF]**
V: 200mV/div. H: 0.1µsec/div.



2 **IC301 - pin 36 [FG]**
V: 1V/div. H: 5msec/div.



3 **IC301 - pin 55 [LOAD_DRV]**
V: 1V/div. H: 500nsec/div.



4 **IC301 - pin 44 [SPDL_PDM]**







5 **CN102 - pin3, 2, 1**
(IC101 - pin 14, 13, 12)
[FTS Driver -A1, A2, A3]



C JCKB ASSY

6 **Foot of R208** (IC201 - pin 5)
[AUDIO DAC -MCLK]



7 **Foot of R207** (IC201 - pin 2, 4)
[AUDIO DAC -BCK]



8 **Foot of R206** (IC201 - pin 1)
[AUDIO DAC -LRCK]



9 **Foot of R206** (IC201 - pin 1)
[AUDIO DAC -LRCK]

10 **Foot of R207** (IC201 - pin 2, 4)
[AUDIO DAC -BCK]

11 **Foot of R202** (IC201 - pin 3, 25)
[AUDIO DAC -DATA]
(Waveform of DATA is unsettled.)



12 **Foot of R733** (IC701 - pin 33)
[Composite Video out]



13 **Foot of R735** (IC701 - pin 25)
[Component Video out -Y]
V: 1V/div. H: 10µsec/div.

14 **Foot of R736** (IC701 - pin 23)
[Component Video out -Pb]
V: 2V/div. H: 10µsec/div.

15 **Foot of R737** (IC701 - pin 21)
[Component Video out -Pr]
V: 2V/div. H: 10µsec/div.



16 **Foot of R734** (IC701 - pin 28)
[S Video out -Y]
V: 1V/div. H: 10µsec/div.

17 **Foot of R732** (IC701 - pin 31)
[S Video out -C]
V: 1V/div. H: 10µsec/div.



A

B

C

D

E

F

4. PCB CONNECTION DIAGRAM
4.1 LOAB ASSY

NOTE FOR PCB DIAGRAMS :

1. Part numbers in PCB diagrams match those in the schematic diagrams.
2. A comparison between the main parts of PCB and schematic diagrams is shown below.

Symbol In PCB Diagrams	Symbol In Schematic Diagrams	Part Name
B C E	B C E B C E	Transistor
B C E	B C E B C E	Transistor with resistor
D G S	D G S D G S	Field effect transistor
		Resistor array
		3-terminal regulator

3. The parts mounted on this PCB include all necessary parts for several destinations.
   For further information for respective destinations, be sure to check with the schematic diagram.
4. View point of PCB diagrams.



SIDE A

SIDE B

A LOAB ASSY
(VNP1910-A)





A

A

4.2 DVDM ASSY

SIDE A

SIDE A

B DVDM ASSY
(VNP1921-A)



SIDE B

SIDE B

B DVDM ASSY
(VNP1921-A)



4.3 JCKB ASSY

SIDE B



C JCKB ASSY
(VNP1919-B)

SIDE A



C

SIDE B


JCKB ASSY VWM
V+5V
V+5A
V+12A
V+3D
V+5A
V+12A

SIDE A


WARNING
THIS PRODUCT CONTACT LEAD IN SOLDER AND CERTAIN ELECTRICAL PARTS CONTAIN CHEMICALS WHICH ARE KNOWN TO THE STATE CALIFORNIA TO CAUSE CANCER, BIRTH DEFECTS OR OTHER REPRODUCTIVE HARM. WASH HANDS AFTER HANDLING. HEALTH & SAFETY CODE SECTION 25249.6 - PROPOSITION 65
2/2
CONTACT SIDE
CMKD-P3X
CN751
78M05
IC101
V+3D
V+12A
V+5V
CN701
JA102
JA801
JA101
Z1
5
4

4.4 FLKY and PWSB ASSYS

SIDE A

D FLKY ASSY
(VNP1901-B)



E PWSB ASSY
(VNP1901-B)

SIDE B

E PWSB ASSY
(VNP1901-B)



D FLKY ASSY
(VNP1901-B)

D E

SIDE A


X101
VWG2417-
VWG2418-
VWG2419-
VWG2420-
VWG2421-
VWG2422-
VWG2423-
FLKY
VWG
PC
S109
EJECT
IR101
VNP1901-
DC FC
北米／欧州
STOP/EJECT
S105
C181
PAUSE/<<
S106
C101
PLAY/>>
S107
S108
/STOP
S117
TOP MENU
S114
S116
LEFT
UP
S113
S115
ENTER
RIGHT
S112
MENU
S111
/PLAY
S110
S118
S119
DOWN
RETURN
HOME MENU/PAUSE
CN101
CN104
CN104
B CN105

SIDE B


CN104
VWG2423-
VWG2422-
VWG2421-
VWG2420-
VWG2419-
VWG2418-
VWG2417-
VNP1901-
FLKY
A
G
H

4.5 POWER SUPPLY UNIT

SIDE A **SIDE B**

F POWER SUPPLY UNIT
[VWR1366]



5. PCB PARTS LIST

NOTES: ● *Parts marked by "NSP" are generally unavailable because they are not in our Master Spare Parts List.*
● *The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.*
● *When ordering resistors, first convert resistance values into code form as shown in the following examples.*
Ex.1 When there are 2 effective digits (any digit apart from 0), such as 560 ohm and 47k ohm (tolerance is shown by J=5%, and K=10%).

560 Ω	→ *56 x 10[1]* →	*561*	*RD1/4PU 5 6 1 J*
47k Ω	→ *47 x 10[3]* →	*473*	*RD1/4PU 4 7 3 J*
0.5 Ω	→	*R50*	*RN2H R 5 0 K*
1 Ω	→	*1R0*	*RS1P 1 R 0 K*

Ex.2 When there are 3 effective digits (such as in high precision metal film resistors).

5.62k Ω	→ *562 x 10[1]* →	*5621*	*RN1/4PC 5 6 2 1 F*

LIST OF ASSEMBLIES

Mark	No.	Description	Part No.
[RDXU/RA, RPWXU, RLXJ/NC, BKXJ and RTXJN types]			
NSP	1	..LOADING MECHA. ASSY	VWT1207
NSP	2	..LOAB ASSY	VWG2426
	1	..DVDM ASSY	VWS1563
	1	..JCKB ASSY	VWV1942
NSP	1	..FLKB ASSY	VWM2194
	2	..FLKY ASSY	VWG2436
NSP	2	..PWSB ASSY	VWG2429
⚠	1	..POWER SUPPLY UNIT	VWR1366
[LFXJ type]			
NSP	1	..LOADING MECHA. ASSY	VWT1207
NSP	2	..LOAB ASSY	VWG2426
	1	..DVDM ASSY	VWS1563
	1	..JCKB ASSY	VWV1946
NSP	1	..FLKB ASSY	VWM2195
	2	..FLKY ASSY	VWG2437
NSP	2	..PWSB ASSY	VWG2429
⚠	1	..POWER SUPPLY UNIT	VWR1366

Mark	No.	Description	Part No.

A LOAB ASSY [VWG2426]

SWITCHES AND RELAYS

	S101	REAF SWITCH	VSK1011

OTHERS

	CN602	CONNCTOR	S2B-PH-K
	CN601	CONNCTOR	S5B-PH-K
		PRINTED CIRCUIT BOARD	VNP1910

B DVDM ASSY [VWS1563]

SEMICONDUCTORS

	IC602		K4S281632D-TC75
	IC702		K4S641632F-TC75
	IC101		M63018FP
⚠	IC401		MM1565AF
⚠	IC402		PQ033EZ01ZP
⚠	IC403		PQ1L333M2SP
	IC400		PST3228
	IC701		SAA7893HL/C2
	IC601		STI5588CVB
	IC301		STM6316ATXXA
	IC608		TC7WH34FU
	IC604, IC606, IC607		TC7WU04FU
	IC603		VYW2087
	Q390, Q501, Q511, Q521, Q531		2SA1576A
	Q541, Q551		2SA1576A
	Q401, Q403		2SA1602A
	Q202, Q212, Q402		2SC4081
	Q6973		DTC114TUA
	Q201, Q211		IMT1A
	Q6302		UMD3N
	Q6972		UMX1N
	D6971		1SS355
	D6301		RB501V-40

COILS AND FILTERS

	L390		LCYA2R7J2520
	L604, L606, L607		LCYA470J2520
	L608		LCYAR22J2520

CAPACITORS

	C309, C315, C318, C319, C323		CCG1179
	C326, C342, C348, C357, C360		CCG1179
	C373, C377, C388, C391, C6004		CCG1179
	C6014, C6047, C6808 (2.2u/6.3V)		CCG1179
	C390		CCSRCH180J50
	C142		CCSRCH221J50
	C200		CCSRCH331J50
	C392		CCSRCH560J50
	C393		CCSRCH7R0D50
	C6402, C6403		CCSRCH8R0D50
	C211		CEVW100M16
	C231, C406, C410, C501, C706		CEVW101M16
	C710, C718		CEVW101M16
	C6015, C6122, C713, C719		CEVW101M4
	C201		CEVW220M16
	C301, C408, C420, C430		CEVW221M4
	C6049, C6050, C6137, C6160		CEVW221M4
	C401		CKSQYB225K10
	C127, C128, C381, C423, C427		CKSRYB102K50
	C433, C6701, C702, C711		CKSRYB102K50

Mark	No.	Description	Part No.
	C112–C114, C124, C125, C205		CKSRYB103K50
	C213, C214, C355, C705, C6124		CKSRYB103K50
	C101, C102, C122, C132, C139		CKSRYB104K16
	C300		CKSRYB104K16
	C394		CKSRYB152K50
	C126, C344		CKSRYB223K50
	C403, C409, C6301, C6812, C707		CKSRYF104Z25
	C230, C232, C233, C411, C412		CKSRYF105Z10
	C424, C434, C435, C502–C507		CKSRYF105Z10
	C6023, C6030, C6037, C6048, C6064		CKSRYF105Z10
	C6081, C6094, C6107, C6119, C6121		CKSRYF105Z10
	C6136, C6149, C6150, C6159		CKSRYF105Z10
	C6171, C6172, C6184, C6198, C6401		CKSRYF105Z10
	C6404, C6703-C6708, C6974, C6975		CKSRYF105Z10
	C701, C703, C704, C708, C709		CKSRYF105Z10
	C712, C714–C717, C720–C725		CKSRYF105Z10
RESISTORS			
	R6017, R6932		RAB4C0R0J
	R201		RAB4C220J
	R211		RAB4C390J
	R109, R402, R403, R408, R409		RS1/10S0R0J
	R412–R416, R420, R421, R424		RS1/10S0R0J
	R427, R480–R482, R488, R6149		RS1/10S0R0J
	R6159, R6305, R6701, R712, R713		RS1/10S0R0J
	R725, R727		RS1/10S0R0J
	R103, R106		RS1/10S1R0J
	R104, R107		RS1/10S1R8J
	R115–R120		RS1/10S4R7J
	R125, R152, R330, R331, R6028		RS1/16S1002F
	R6035		RS1/16S1002F
	R301		RS1/16S1202F
	R502, R512, R522, R532, R542		RS1/16S1500F
	R552		RS1/16S1500F
	R101, R102, R123, R172, R182		RS1/16S5600F
	Other Resistors		RS1/16S###J
OTHERS			
	CN401 PH CONNECTER(SMT)		S13B-PH-SM3
	CN103 PH CONNECTER(SMT)		S5B-PH-SM3
	FLEXIBLE CABLE		VDA1681
	CN104 4P CONNECTOR		VKN1409
	CN102 12P CONNECTOR		VKN1416
	CN105 21P CONNECTOR		VKN1425
	CN101 24P CONNECTOR		VKN1464
	CN601, CN602 33P CONNECTOR		VKN1519
	KN102 EARTH METAL FITTING		VNF1109
	KN103 EARTH METAL FITTING		VNF1109
	X6401 (27MHz)		VSS1172
	X301 (20MHz)		VSS1186

C JCKB ASSY [VWV1942]

Mark	No.	Description	Part No.
SEMICONDUCTORS			
	IC204, IC302, IC402		BA4560F
	IC301, IC401		DSD1702EG
	IC201		DSD1791DBR
	IC701		LA73054
⚠	IC771		MM1565AF
⚠	IC101		NJM78M05FA
	IC103, IC104		TC7WU04F
	Q203, Q216, Q303, Q403		2SA1576A
	Q101, Q801		2SC4081
	Q205–Q208, Q304, Q305		2SD2114K
	Q404, Q405		2SD2114K
	Q201, Q202, Q214, Q215		DTC114YUA
	Q301, Q302, Q401, Q402, Q702		DTC114YUA
	D101, D601		1SS355
	D102		UDZS6.2B
COILS AND FILTERS			
	L701, L702 CHIP BEADS		VTL1089
	L801 CHIP BEADS		VTL1108
CAPACITORS			
	C327, C328, C427, C428		CCSRCH151J50
	C206, C303, C403		CCSRCH331J50
	C621, C624		CCSRCH470J50
	C302, C308, C321, C322, C402		CEAT101M10
	C408, C421, C422		CEAT101M10
	C232, C330, C430		CEAT101M16
	C712, C713, C718		CEAT102M6R3
	C205		CEAT220M50
	C109, C116, C201, C203, C304		CEAT331M10
	C404		CEAT331M10
	C245, C246, C331, C332		CEAT470M16
	C431, C432		CEAT470M16
	C719, C720		CEAT471M6R3
	C102, C118, C732, C771		CEJQ101M16
	C804		CEJQ1R0M50
	C105, C111, C707, C711, C730		CEJQ221M6R3
	C743, C774, C805		CEJQ221M6R3
	C702–C706, C773		CKSQYB225K10
	C701		CKSQYF104Z25
	C117, C202, C210, C212, C301		CKSRYB102K50
	C401, C734, C737		CKSRYB102K50
	C323, C324, C423, C424		CKSRYB152K50
	C204, C207–C209, C231, C305		CKSRYF104Z25
	C329, C405, C429, C714, C801		CKSRYF104Z25
	C806		CKSRYF104Z25
	C101, C106, C108, C112–C115		CKSRYF105Z10
	C211, C247, C248, C306		CKSRYF105Z10
	C325, C326, C406, C425, C426		CKSRYF105Z10
	C623, C708–C710, C731, C733		CKSRYF105Z10
	C736, C742, C772		CKSRYF105Z10
	C234, C236		CQMBA152J50
	C238, C240, C242, C244		CQMBA561J50
RESISTORS			
	R323, R326, R423, R426		RN1/16SE1502D
	R231, R234, R238, R242		RN1/16SE1801D
	R232, R237, R239, R244		RN1/16SE3301D
	R321, R322, R421, R422		RN1/16SE8201D
	R271, R282, R361, R461		RS1/10S332J
	R706, R707		RS1/10S68R0F
	R324, R325, R424, R425		RS1/16S1001F
	R233, R235, R240, R243		RS1/16S6800F
	R704, R708–R710		RS1/16S68R0F
	R805		RS1/16S75R0F
	Other Resistors		RS1/16S###J
OTHERS			

Mark	No.	Description	Part No.
	JA801	OPT. LINK OUT 12MB/S	GP1FA502TZ
	JA601, JA602	JACK	RKN1004
	JA101	JACK	VKB1167
	JA102	JACK	VKB1179
	CN601	7P CONNECTOR	VKN1211
	CN101, CN102	33P CONNECTOR	VKN1519
	KN101–KN103	EARTH METAL FITTING	VNF1084

C JCKB ASSY [VWV1946]

SEMICONDUCTORS

	IC204, IC302, IC402	BA4560F
	IC301, IC401	DSD1702EG
	IC201	DSD1791DBR
	IC701	LA73054
⚠	IC771	MM1565AF
⚠	IC101	NJM78M05FA
	IC103, IC104	TC7WU04F
	Q203, Q216, Q303, Q403	2SA1576A
	Q101, Q801	2SC4081
	Q205–Q208, Q304, Q305	2SD2114K
	Q404, Q405	2SD2114K
	Q201, Q202, Q214, Q215	DTC114YUA
	Q301, Q302, Q401, Q402, Q702	DTC114YUA
	D101, D601	MA111
	D102	UDZS6.2B

COILS AND FILTERS

	L701, L702	CHIP BEADS
	L801	CHIP BEADS

CAPACITORS

	C327, C328, C427, C428	CCSRCH151J50
	C206, C303, C403	CCSRCH331J50
	C621, C624	CCSRCH470J50
	C302, C308, C321, C322, C402	CEAT101M10
	C408, C421, C422	CEAT101M10
	C232, C330, C430	CEAT101M16
	C712, C713, C718, C724	CEAT102M6R3
	C205	CEAT220M50
	C109, C116, C201, C203, C304	CEAT331M10
	C404	CEAT331M10
	C245, C246, C331, C332	CEAT470M16
	C431, C432	CEAT470M16
	C719, C720, C725, C726	CEAT471M6R3
	C102, C118, C732, C771	CEJQ101M16
	C804	CEJQ1R0M50
	C105, C111, C707, C711, C730	CEJQ221M6R3
	C743, C774, C805	CEJQ221M6R3
	C702–C706, C773	CKSQYB225K10
	C701	CKSQYF104Z25
	C117, C202, C210, C212, C301	CKSRYB102K50
	C401, C734, C737	CKSRYB102K50
	C323, C324, C423, C424	CKSRYB152K50
	C204, C207–C209, C231, C305	CKSRYF104Z25
	C329, C405, C429, C714, C801	CKSRYF104Z25
	C806	CKSRYF104Z25
	C101, C106, C108, C112–C115	CKSRYF105Z10
	C211, C247, C248, C306	CKSRYF105Z10
	C325, C326, C406, C425, C426	CKSRYF105Z10
	C623, C708–C710, C731, C733	CKSRYF105Z10
	C736, C742, C772	CKSRYF105Z10
	C234, C236	CQMBA152J50
	C238, C240, C242, C244	CQMBA561J50

RESISTORS

	R323, R326, R423, R426	RN1/16SE1502D
	R231, R234, R238, R242	RN1/16SE1801D
	R232, R237, R239, R244	RN1/16SE3301D
	R321, R322, R421, R422	RN1/16SE8201D
	R271, R282, R361, R461	RS1/10S332J
	R706, R707	RS1/10S68R0F
	R324, R325, R424, R425	RS1/16S1001F
	R233, R235, R240, R243	RS1/16S6800F
	R704, R708–R713	RS1/16S68R0F
	R805	RS1/16S75R0F
	Other Resistors	RS1/16S###J

OTHERS

	CN701	D-SOCKET(14P)
	JA801	OPT. LINK OUT 12MB/S
	JA601, JA602	JACK
	JA101	JACK
	JA102	JACK
	CN601	7P CONNECTOR
	CN101, CN102	33P CONNECTOR
	KN101–KN103	EARTH METAL FITTING

	AKP7137	
	GP1FA502TZ	
	RKN1004	
	VKB1167	
	VKB1179	
	VKN1211	
	VKN1519	
	VNF1084	

D FLKY ASSY [VWG2436]

SEMICONDUCTORS

IC101	PE5374A
D102	SLR-343VC

SWITCHES AND RELAYS

S102–S107, S109–S118	ASG7013

CAPACITORS

C183, C199	CKSRYB102K50
C151–C153	CKSRYB103K50
C102, C105	CKSRYF104Z25
C104	CKSRYF104Z50
C182	CKSRYF105Z10

RESISTORS

All Resistors	RS1/16S###J

OTHERS

CN102	CONNECTOR POST	B3B-PH-K
IC104	REMOTE RECEIVER	RPM7240-H4
V101	FLUORESCENT TUBE	VAW1078
CN104	21P CONNECTOR	VKN1225
X101	(5MHz)	VSS1142

D FLKY ASSY [VWG2437]

SEMICONDUCTORS

IC101	PE5374A
D102	SLR-343VC

SWITCHES AND RELAYS

S102–S107, S109–S118	ASG7013

CAPACITORS

C183, C199	CKSRYB102K50
C151–C153	CKSRYB103K50

Mark	No.	Description	Part No.
	C102, C105		CKSRYF104Z25
	C104		CKSRYF104Z50
	C182		CKSRYF105Z10

RESISTORS

	All Resistors	RS1/16S###J

OTHERS

	CN102 CONNECTOR POST	B3B-PH-K
	IC104 REMOTE RECEIVER	RPM7240-H4
	V101 FLUORESCENT TUBE	VAW1076
	CN104 21P CONNECTOR	VKN1225
	X101 (5MHz)	VSS1142

E PWSB ASSY [VWG2429]

SWITCHES AND RELAYS

	S101	ASG7013

OTHERS

	CN103 CONNECTOR POST	B3B-PH-K

F POWER SUPPLY UNIT [VWR1366]

OTHERS

⚠	P301 PROTECTOR(800mA)	AEK7063
⚠	P101 PROTECTOR(1.6A)	AEK7066

6. ADJUSTMENT

6.1 ADJUSTMENT ITEMS AND LOCATION

■ Adjustment Items

[Mechanism Part]

❶ Tangential and Radial Height Coarse Adjustment

❷ DVD Jitter Adjustment

[Electrical Part]

Electrical adjustments are not required.

■ Adjustment Points (Mechanism Part)

Cautions: After adjustment, adjustment screw locks with the Screw tight.



6.2 JIGS AND MEASURING INSTRUMENTS

 ⊕ Screwdriver (large)	 ⊕ Screwdriver (medium)	 TV monitor	 Test mode remote control unit (GGF1381)
 ⊕ Precise screwdriver	 DVD test disc (GGV1025)	 Soldering iron	Screw tight (GYL1001)

6.3 NECESSARY ADJUSTMENT POINTS

When	Adjustment Points	
■ Exchange Parts of Mechanism Assy		
Exchange the Pickup	Mechanical point	❶, ❷ ＊ After adjustment, screw locks with the Screw tight.
	Electric point	———
Exchange the Traverse Mechanism	Mechanical point	———
	Electric point	———
Exchange the Spindle Motor	Mechanical point	❷ ＊ After adjustment, screw locks with the Screw tight.
	Electric point	———
■ Exchange PCB Assy		
Exchange PC Board LOAB and DVDM ASSYS	Mechanical point	———
	Electric point	———

6.4 TEST MODE

• The TEST MODE functions that are used only during adjustment are described here. For details, see "7.1.1 TEST MODE".

TEST MODE: ON



TEST MODE: DISC SET

<TRAY OPEN>



TEST MODE: PLAY

<PLAY>



CAUTION:
Perform only trace, video and audio outputs are nothing.

< When playback with the target address of disc (DVD)>

For example, when playback with # 30000

During PLAY [+10] ➡ [3] ➡ [0] ➡ [0] ➡ [0] ➡ [0] ➡ [CHP/TIM] Press keys in order



TEST MODE: OFF



6.5 MECHANISM ADJUSTMENT

1 Tangential and Radial Height Coarse Adjustment

START

- Remove the Loading Mecha. Assy.
- Remove a Spacer for height adjustment attached to the back side (shaded area) of the Loading Mecha. Assy (Float Base) with nippers.



Note:
Before removing the flexible cable for the pickup, soldering of the pickup circuit is necessary.
For details, see "7.1.10 DISASSEMBLY".

Cautions:
Because there is not a Spacer for height adjustment in adjustment after the second time, will keep it at need.
(This parts is Traverse mechanism exclusive use of a model for 2003 years)



Put a spacer between a Tangential (or Radial) adjustment screw and Mechanism Base and turn each screw to adjust the height. (Refer to "6.1 ADJUSTMENT ITEMS AND LOCATION".)



2 DVD Jitter Adjustment

- Playback method of inner and outer address for the purpose is refererd to "6.4 TEST MODE".
- Jitter indication of the monitor is refererd to "7.1.2 DISPLAY SPECIFICATION OF THE TEST MODE".

Use disc: GGV1025



7. GENERAL INFORMATION

7.1 DIAGNOSIS

7.1.1 TEST MODE

■ Test Mode Functional Specification

① Test mode entry

In the power ON state, press the [ESC] (A8-5F) key and [TEST / RANDOM] (A8-5E) key in order of the Test mode remote control unit.

- Light the all FL and LEDs, and goes out the FL and LEDs when pressing the keys of something.
- OSD displays test mode. Refer to the "7.1.2 DISPLAY SPECIFICATION OF THE TEST MODE".

② Release the Test mode

- Turn off the power.
- Press the [ESC] (A8-5F) key of the remote control unit and reset it.

③ Tray open / close

- Press the [REPEAT A-B] (A8 - 48) key of the remote control unit.
- Press the [OPEN / CLOSE] key of the main unit from the stop state.

④ Playback stop

1. Press the [REPEAT] (A8 - 44) key of the remote control unit from the playback state.
2. Press the [STOP] key of the remote control unit or main unit from the playback state.
   (Playback stops, but the loaded disc keeps rotating.)

⑤ LD ON

DVD : Press the [TEST] (A8-5E) and [1] (A8-01) keys in order, and turn on the laser diode (650n).
CD : Press the [TEST] (A8-5E) and [4] (A8-04) keys in order, and turn on the laser diode (780n).

⑥ Focus on / sweep

1. Lock the focus by pressing the [TEST] (A8-5E) and [2] (A8-02) keys in order.
2. Repeat focus sweep by pressing the [TEST] (A8-5E) and [3] (A8-03) keys in order.

⑦ Spindle FG servo

CAV : Press the [TEST] (A8-5E) and [5] (A8-05) keys in order,then rise up the spindle and FG servo becomes on.
CLV : Press the [TEST] (A8-5E) and [9] (A8-09) keys in order,then rise up the spindle and FG servo becomes on.

⑧ Tracking open / close

1. Open tracking by pressing the [STEP FWD] (A8-54) key of the remote control unit in the play state.
2. Close tracking by pressing the [STEP REV] (A8-50) key of the remote control unit in the play state.

⑨ Slider servo on/off

1. Turn on the slider servo by pressing the [TEST] (A8-5E) and [CX] (A8-0E) keys in order.
2. Turn off the slider servo by pressing the [TEST] (A8-5E) and [TV/LDP] (A8-0F) keys in order.

⑩ Slider in / out

Slider in : In the tracking off state, press the [SCAN REV] (A8-11) key of the remote control unit.
Slider out : In the tracking off state, press the [SCAN FWD] (A8-10) key of the remote control unit.

⑪ Play (perform only the ID search and trace to the specified location)

Press the [TV/LDP] (A8-0F) key of the remote control unit from the stop state.
Perform only trace, video and audio outputs are nothing.

⑫ Screen display ON/OFF

1. Turn off the display by pressing the [AUDIO] (A8-1E) key of the remote control unit.
2. Turn on the display by pressing the [DISPLAY] (A8-43) key of the remote control unit.

⑬ Search

1. Search address input entry

- It becomes the address input mode when pressing the [+10] (A8-1F) key. (Most significant digit of an address displays "<".)
- In this time, display the last address as the initial state.

2. Search address input

- Press the [0] to [9] (A8-00 to 09) keys of the remote control unit. In the DVD, set an address with hexadecimal.
- In the address input mode, turn to the hexadecimal input by pressing the [PROGRAM] (A8-4C) key (display a "∗" mark), and [1] to [6] keys are each input as A to F.
- Hexadecimal input and decimal input can switch with toggle.
- In case of CD, perform only the absolute time search.

3. Search execution

- Press the [CHP/TM] (A8-13) key of the remote control unit.
- After the search, perform only trace and video and audio outputs are nothing.

4. Release the Search address input

- Clear the address by pressing the [CLEAR] (A8-45) key. Release the address input mode when pressing the [CLEAR] key once again.

7.1.2 DISPLAY SPECIFICATION OF THE TEST MODE



① **Address indication**
The address being traced is displayed in number.
(as for the DVD, indication of decimal number is possible.)
DVD : ID indication (hexadecimal number, 8 digits)
[＊＊＊＊＊＊＊＊]
CD : A-TIME (min. sec.) [0 0 0 0 ＊＊＊＊]

② **Code indication of remote control unit [R – ＊＊＊＊]**
In case of double code, display a 2nd code.

③ **Main unit keycode indication [K – ＊＊]**

⑤ **Tracking status [TRKG – ＊＊＊]**
Tracking on : [ON]
Tracking off : [OFF]

⑥ **Spindle status [SPDL – ＊＊＊]**
[OFF], [ACC/BRK], [CAV], [CLV]

⑦ **Mechanism (loading) position value [M – ＊＊]**
Unknown : [01] or [41]
Open state : [04]
Close state : [08]
During opening : [12]
During closing : [22]

⑧ **Slider position [S – ＊＊＊＊]**
In Side Switch ON : [01]
In Side Switch OFF : [00]

⑨ **Output video system [V – ＊＊＊＊]**
NTSC system : [NTSC]
PAL system : [PAL]
Automatic setting : [AUTO]

Scart terminal output [SK – ＊＊]
(Display only the WY model which can do the output setting of scart terminal.)
VIDEO : [00]
S-VIDEO : [01]
RGB : [02]

⑩ **Disc sensing [DSC – ＊＊＊]**
The type of discs loaded is displayed.
[DVD], [CD], [VCD], [ ]

⑪ **Jitter value [J – ＊＊＊＊]**

⑫ **Version of the AV-1 chip / version of firmware [AV: ＊＊ / ＊＊＊＊＊＊＊＊]**

⑬ **Version of the FL controller [FL: ＊＊＊＊]**

⑭ **Region setting of the player [REG: ＊]**
Setting value : [1] to [6]

⑮ **Destination setting of the FL controller [MDL: ＊＊＊＊ / ＊＊＊]**
Four characters in the front represent the type of model.
Three characters in the back represent the destination code.
J: /J, K: /KU, /KC, /KU/KC, R: /RL/RD, RAM : /RAM,
LB: /LB, WY: /WY

⑯ **Part number of the flash ROM and system controller [＊＊＊＊＊＊ / ＊＊＊＊＊＊]**

⑰ **Version of the flash ROM [V: ＊. ＊＊＊]**
Flash ROM size [FLASH = ＊＊]

⑱ **Revision of the system controller [S: ＊. ＊＊＊ / ＊. ＊＊＊]**
version . revision / build number of the ST core

⑲ **Revision of the DVD mechanism controller [M: ＊＊ / ＊＊＊]**
Kinds of version / firmware of the FE.
RAM or ROM

7.1.3 FUNCTIONAL SPECIFICATION OF THE SHORTCUT KEY

Only during normal playback, the following shortcut keys can be assigned by pressing a required key after pressing the ESC key of the remote control unit. To quit, press the ESC key

Command Contents	Conditions	Remote Control Key Name	Remote Control Code
Memory clear and resion / revision indication		CLEAR (∗1)	A8-45
Average value measurement of DVD error rate		5 (∗1)	A8-05
CD error rate measurement		5 (∗1)	A8-05
Aspect : Pan scan		2	AF-A2
Aspect : Letter box		3	AF-A3
Aspect : Wide		4	AF-A4
Digital : AC3		5	AF-A5
Digital : AC-3 > PCM		6	AF-A6
Virtual surround : OFF	Only for models having the corresponding functions	7	AF-A7
Virtual surround : TruSurround		8	AF-A8
Digital output ON		REPEAT A	AF-E8
Digital output OFF		REPEAT B	AF-E4
DTS Digital output ON	Step-up mode : DTS Out	STEP FWD	AF-B7
DTS Digtal output OFF	Step-up mode : DTS >Out	STEP REV	AF-B8
Scart terminal output : VIDEO	WY, models equipped with Scart terminal	AUDIO	AF-BE
Scart terminal output : S-VIDEO		SUBTITLE	AF-36
Scart terminal output : RGB		ANGLE	AF-B5
Progressive OFF	Only for progressive models (This command is valid in the stop state after the playback.)	R_SKIP	A3-9D
Progressive ON		F_SKIP	A3-9C
SACD multi audio select play ON	Only for SACD models (This command is valid in the stop state after the tray closed.)	K_ADSEL (DIG/ANA)	A8-0C
SACD multi audio select play OFF		LAS_MEMO	AF-F6
SACD hibrid SACD CD layer ON		KD_PLUS10	AF-BF
SACD hibrid SACD CD layer OFF		CONDITION	AF-B1
Audio 5.1 CH ON	Only for models having the corresponding functions (This command is valid in stop state.)	KD_ENTER	AF-EF
Audio 5.1 CH OFF		SURROUND	AF-61
FL indication of EDC / ID error		CX (∗1)	A8-0E
FL indication of ID number		STEREO (∗1)	A8-4A
ZOOM ON (X4)		ZOOM	AF-37
ZOOM OFF		<X3 (∗1)	A8-59
Service mode indication (error rate indication, etc.)		CHP/TIM (∗1)	A8-13
Model information indication		CHAP (∗1)	A8-40
Background color change		+10 (∗1)	A8-1F
Audio last stage mute ON		9	A8-A9
Audio last stage mute OFF		0	AF-A0
Title search Input mode IN Title No. input Search execution		SIDE A (∗1) Numbers (∗1) PLAY (∗1)	A8-4D A8-00 to A8-09 A8-17
Region confimation mode		AUDIO (∗1) Numbers (∗1)	A8-1E A8-01 to A8-08

∗1 : Test mode remote control unit

• Service mode indication (ESC + CHP/TIM keys)
ID Address
The error rate is always displayed in exponential notation, e.g., ∗.∗ ∗ e - ∗, for both DVDs and CDs.
EDC/ID/AV 1 error history (ID Address, EDC/ID/AV 1 Error, last eight errors)
Self-diagnosis functions (If a mechanical error has occurred, the mechanical-error history is also displayed.)

• Calculation of the average error rate (ESC + "5" [Test mode remote control unit] keys)
The average of the last eight error rates is calculated and indicated in exponential notation. After the calculation is completed, "OK" or "NG" is displayed. If "NG" is displayed, the disc tray will open (for both DVDs and CDs)
For DVDs: OK with 5.0e-4 or less, for CDs: OK with 7.6e-3 or less

• Indication of model information (ESC + CHAP keys)
The items from 12 to 19 of the TEST MODE Indications are displayed. However, in the indications, S in the standard test mode is changed to B.E VERSION, and M is changed to F.E VERSION. For details, see 7.1.4.

• Change of the background colors (ESC + "+10" [Test mode remote control unit] keys)
Every time the keys are pressed, the background color is changed between blue and green alternately.
(The green background is used in SETUP NAVIGATOR.)

• Region confirmation mode (ESC + AUDIO [Test mode remote control unit] + "1"-"8" [Test mode remote control unit] keys)
After you press the AUDIO key while holding the ESC key pressed and then input the region number, if the number is different from that set in the unit, an error message is displayed, and the tray opens.

7.1.4 SPECIFICATION OF MODEL INFORMATION DISPLAY

To display model information : Press the ESC key then the CHAP key.
To close the model information display : Press the ESC key.

• Display contents



Character in bold : Item name
□: Information display

① **Model name**
Display it according to model information set from the FL controller.
② **Destination indication**
Display it according to model information set from the FL controller.
③ **Region No.**
④ **Part number**
⑤ **ROM version**
⑥ **Flash size**
⑦ **FL controller version**

⑧ **CHIP VERSION**
Version of ST CHIP
CUT ID / JTAG ID
(two columns) (eight columns)

⑨ **B.E VERSION**
Version of BACK END (version of ST core software)
□.□ /□□□
softwareVersion . softwareRevision / buildNumber

⑩ **F.E VERSION**
Version of FRONT END (version of mechanism controller CHIP software)
□□/ □
MainVersion / Kinds of firmware RAM or ROM

⑪ **Remote control code**
⑫ **Key code of Main unit**

7.1.5 FUNCTIONAL SPECIFICATION OF THE SERVICE MODE

• EDC / ID error FL display (shortcut function)

EDC/ID error is displayed on the FL display if you press the CX key while holding the ESC key on the TEST MODE remote control unit pressed. To quit while an EDC/ID error is displayed, press the ESC key.

FL display

0 0 / 0 0 / 0 1 ∗

∗: Lights when an AV1 error was generated at least once.

Number of sites where an EDC or ID error was generated

Number of retrials while an ID error is being generated
(only displayed at the moment when an error is being generated),
and for the ST models, the number of retrials made for the latest ID error

Number of retrials while an EDC error is being generated
(only displayed at the moment when an error is being generated),
and the number of retrials made for the latest EDC error

• Display during Service Mode

To enter Service Mode, press the CHP/TIM key while holding the ESC key pressed.
To quit, press the ESC key.

Service mode display

① ID Address

② Error rate (always displayed), in exponential notation

∗∗ (∗∗∗∗)

Number of error rates

02: Indicates use of the same method as for the 02 models,
No indication: Indicates use of the method used for models before the 02 model

③ EDC/ID/AV1 error history (ID Address, EDC/ID/AV1 errors, last eight errors)

Description of AV1 errors
BIT0: In BE code, an EDC error, FEC I/F buffer overflow, or "not valid" is generated (B.E error)
BIT1: In BE code, the ID is different from that of the target (B.E error)
BIT2: An error was generated in FE-added 2-byte EDC data. (F.E error)

④ Self-diagnosis functions

Whether F.E is normal or not is checked.

FE OK: No abnormality in F.E

FE Error: Abnormality is recognized in F.E.
Pressing the CHP/TIM key again displays the mechanical error history. Each press of the CHP/TIM key changes the displays between the mechanical error history and the Service Mode display.
For details on the mechanical error history, refer to the addendum.

Indication plan contents

AV1 ERR	BIT 2	1	0
00	0	0	0
01	0	0	1
02	0	1	0
03	0	1	1
04	1	0	0
05	1	0	1
06	1	1	0
07	1	1	1

Character in bold : Item name
□: Information display

7.1.6 MECHANICAL ERROR HISTORY

Only if a mechanical error (FE error) has been generated, a mechanical error history containing up to the last eight errors is displayed if you press the CHP/TIM key in Service Mode.
Errors are displayed in descending order, with the latest one at the top.

Description of the mechanical error history

① Error number
The first two digits are for the error code, and the second two digits are for the servo state.



② Error number
The elapsed time[µsec] from the time when the system was turned on until an error was generated is displayed.
Note: If a later error time is shorter than the previous error time, it means that the unit was turned off then on again.

③ Description of errors
Error messages are displayed.
Example: If the error code is 0x13 (Focus lost timeout) and the servo state is 0x05 (Disc judge), the message becomes "Focus lost timeout in Disc judge."

Note: When an error has been generated, if the servo state is "Disc judge," the disc tray opens, and if the servo state is other than "Disc judge," the unit stops (excluding a case of a device error with the error code 0xd∗).

Indication contents



• List of the error codes

FOCUS ERROR	0x0∗	**FOCUS TIMEOUT**	0x1∗
Focus on error	0x01	Focus on timeout	0x11
Focus off error	0x02	Focus off timeout	0x12
Focus lost error	0x03	Focus lost timeout	0x13
Focus balance adjust error	0x04	Focus balance adjust timeout	0x14
Focus gain adjust error	0x05	Focus gain adjust timeout	0x15
Focus sweep error	0x06	Focus sweep timeout	0x16
TRACKING ERROR	0x2∗	**TRACKING TIMEOUT**	0x3∗
Tracking on error	0x21	Tracking on timeout	0x31
Tracking off error	0x22	Tracking off timeout	0x32
Tracking lost error	0x23	Tracking lost timeout	0x33
Tracking balance adjust error	0x24	Tracking balance adjust timeout	0x34
Tracking gain adjust error	0x25	Tracking gain adjust timeout	0x35
STEPPING ERROR	0x4∗	**STEPPING TIMEOUT**	0x5∗
Stepping on error	0x41	Stepping on timeout	0x51
Stepping off error	0x42	Stepping off timeout	0x52
Stepping lost error	0x43	Stepping lost timeout	0x53
Stepping move error	0x44	Stepping move timeout	0x54
SPINDLE ERROR	0x6∗	**SPINDLE TIMEOUT**	0x7∗
Spindle on error	0x61	Spindle on timeout	0x71
Spindle off error	0x62	Spindle off timeout	0x72
Spindle lost error	0x63	Spindle lost timeout	0x73
Spindle CAV error	0x64	Spindle CAV timeout	0x74
Spindle CLV error	0x65	Spindle CLV timeout	0x75
ACQUISITION ERROR	0x8∗	**ACQUISITION TIMEOUT**	0x9∗
PLL lost error	0x83	PLL lost timeout	0x93
DECODER ERROR	0xa∗	**DECODER TIMEOUT**	0xb∗
ID lost error	0xa3	ID lost timeout	0xb3
		FAIL SAFE	0xe∗
		Unexpected error	0xe1

• List of the servo states

0x00	Reset
0x01	Stop (inside position)
0x02	Stop (any position)
0x03	Braking for stop
0x04	New disc
0x05	Disc judge
0x06	Reserved 1
0x07	Playing
0x08	Start up
0x09	Seeking
0x0A	Pausing
0x0B	Reading BCA
0x0C	Reserved 2
0x0D	
0x0E	Tray open
0x0F	Tray moving

Note : 0 x □ □
code
(Only this part is displayed to a display)

ERROR CODE TABLE

Error Name	No.	Causes	Check Item	Possibility of Trouble	Remarks
FOCUS ERROR (0 x 0*)					
Focus on error	0 x 01	Focus on could not be completed	Are not there a dirt or a scratch in the Disc? Does LD become weak? Does the lens move up and down?	1. Pickup 2. Driver 3. Front End IC	
Focus off error	0 x 02	Focus off could not be completed	Unknown		
Focus lost error	0 x 03	Focus servo is lost	Are not there a dirt or a scratch in the Disc? Does LD become weak?	1. Pickup	
Focus balance adjust error	0 x 04	AFB on could not be completed			
Focus gain adjust error	0 x 05	Focus AGC could not be completed			
Focus sweep error	0 x 06				
FOCUS TIMEOUT (0 x 1*)					
Focus on timeout	0 x 11	Did timeout at focus on	Are not there a dirt or a scratch in the Disc? Does LD become weak? Does the lens move up and down?	1. Pickup 2. Driver 3. Front End IC	
Focus off timeout	0 x 12	Did timeout at focus off			
Focus lost timeout	0 x 13	Did timeout at focus backup			
Focus balance adjust timeout	0 x 14	Did timeout at AFB			
Focus gain adjust timeout	0 x 15	Did timeout at AGC			
Focus sweep timeout	0 x 16				
TRACKING ERROR (0 x 2*)					
Tracking on error	0 x 21	Tracking on could not be completed		1. Pickup 2. Driver 3. Front End IC	
Tracking off error	0 x 22	Tracking off could not be completed			
Tracking lost error	0 x 23	Tracking servo is lost		1. Pickup	
Tracking balance adjust error	0 x 24	ATB could not be completed		1. Pickup	
Tracking gain adjust error	0 x 25	AGC could not be completed		1. Pickup	
Tracking jump error	0 x 26	Tracking jump could not be completed			
TRACKING TIMEOUT (0 x 3*)					
Tracking on timeout	0 x 31	Did timeout at tracking on	Are not there a dirt or a scratch in the Disc?	1. Pickup 2. Driver 3. Front End IC	
Tracking off timeout	0 x 32	Did timeout at tracking off			
Tracking lost timeout	0 x 33	Did timeout at tracking backup	Are not there a dirt or a scratch in the Disc?	1. Pickup	
Tracking balance adjust timeout	0 x 34	Did timeout at ATB		1. Pickup	
Tracking gain adjust timeout	0 x 35	Did timeout at AGC		1. Pickup	
Tracking jump timeout	0 x 36	Did timeout at tracking jump			
STEPPING ERROR (0 x 4*)					
Stepping on error	0 x 41	Stepping on could not be completed		1. Pickup 2. Driver 3. Front End IC	
Stepping off error	0 x 42	Stepping off could not be completed			
Stepping lost error	0 x 43	Stepping servo is lost			
Stepping move error	0 x 44	Stepping could not move	Do move to inner and outer periphery of the stepping in the test mode? Do indicate "S-04" at the most inner periphery of the stepping?	1. Stepping motor 2. Inside switch 3. Driver	
STEPPING TIMEOUT (0 x 5*)					
Stepping on timeout	0 x 51	Did timeout at stepping on		1. Pickup 2. Driver 3. Front End IC	
Stepping off timeout	0 x 52	Did timeout at stepping off			
Stepping lost timeout	0 x 53	Did timeout at stepping backup			
Stepping move timeout	0 x 54	Did timeout at stepping movement	Do move to inner and outer periphery of the stepping in the test mode? Do indicate "S-04" at the most inner periphery of the stepping?	1. Stepping motor 2. Inside switch 3. Driver	

Error Name	No.	Causes	Check Item	Possibility of Trouble	Remarks
SPINDLE ERROR (0 x 6∗)					
Spindle on error	0 x 61	Spindle on could not be completed			
Spindle off error	0 x 62	Spindle off could not be completed			
Spindle lost error	0 x 63	Spindle lost control			
Spindle CAV error	0 x 64	CAV on could not be completed			
Spindle CLV error	0 x 65	CLV on could not be completed			
SPINDLE TIMEOUT (0 x 7∗)					
Spindle on timeout	0 x 71	Did timeout at spindle on			
Spindle off timeout	0 x 72	Did timeout at spindle stop			
Spindle lost timeout	0 x 73	Did timeout at spindle backup	Are not there a dirt or a scratch in the Disc? Is FG output from the driver?	1. Spindle motor 2. Spindle driver	
Spindle CAV timeout	0 x 74	Did timeout at CAV on	Is spindle rotating? Is FG output from the driver? Is the PDM output from Front End?	1. Spindle motor 2. Spindle driver 3. Front End IC	
Spindle CLV timeout	0 x 75	Did timeout at CLV on			
ACQUISITION ERROR (0 x 8∗)					
PLL lost error	0 x 83	PLL is lost	Are not there a dirt or a scratch in the Disc?	1. Pickup 2. Front End IC	
ACQUISITION TIMEOUT (0 x 9∗)					
PLL lost timeout	0 x 93	Did timeout at PLL backup	Are not there a dirt or a scratch in the Disc?	1. Pickup 2. Front End IC	
DECODER ERROR (0 x a∗)					
ID lost error	0 x a3	ID is not readable	Are not there a dirt or a scratch in the Disc?	1. Pickup 2. Front End IC	
DECODER TIMEOUT (0 x b∗)					
ID lost timeout	0xb3	Did timeout at ID backup	Are not there a dirt or a scratch in the Disc?	1. Pickup 2. Front End IC	
FAILSAFE (0 x e∗)					
Unexpected error	0 x e1	Unexpected error		1. Hardware broken 2. Software bug	

7.1.7 ID NUMBER AND ID DATA SETTING

Caution:
For the DVD players compatible with DVD-RW, for playback of a DVD-RW disc (CPRM), it is necessary that an individual ID number and ID data are set for each player. If the ID number and ID data be not properly set in the manner described below, future operations cannot be guaranteed. The ID number is written on the yellow label at the rear panel of the player.
If there is no yellow label, before downloading FLASH ROM, take note of the ID number set following the procedures outlined in "ID Number Confirmation Mode" on the next page.

Note: Enter ID numbers while the unit is in Stop mode so that the values set will be immediately written to the flash ROM. The following operations are all made with the TEST MODE remote control unit (GGF1381).

■ ID Number Input Mode

① To enter ID Number Input Mode, with no ID number set, such as in a case of immediately after upgrading the firmware, press the ESC key then the STEREO key.

Note: If a previous ID number and ID data, such as a factory-preset ID number and ID data, are maintained, the unit enters ID Number Confirmation Mode when the above keys are pressed. However, if only an ID number is maintained, the unit enters ID Data Input Mode.

② Enter a 9-digit ID number. The ID number is also displayed on the FL display.

③ By pressing the CLEAR key without having input a number, you can exit this mode. Each press of this key after a number has been input deletes one digit.

```
[Player's ID Number Setting]
 ID Number ?
② > - - - - - - - - -

③ <CLEAR>  Exit


 Input ID Number !
```

④ After entering all 9 digits, if you press the PLAY key, the unit enters Compare mode. Enter the same ID number again. Only if your two input numbers match, the ID number is set. Compare mode helps eliminate mistyping of the ID number.

Note: If you press the PLAY button before inputting a 9-digit ID number, the unit returns to Step ② without doing anything else.

⑤ After entering all 9 digits, if you press the SEARCH key, the unit unconditionally sets the input number as the ID number. Then the unit automatically enters Player's Data Input Mode. (The SEARCH key is not accepted after all 9 digits have been entered.)

```
[Player's ID Number Setting]
 ID Number ?
 > 0 0 0 0 0 0 0 0 1   OK ?

④ <PLAY>      Compare Mode
⑤ <SEARCH>  Enter

 Input ID Number !
```

⑥ This display appears when the PLAY key is pressed in Step 4. Enter a 9-digit number to compare. The number is also displayed on the FL display.

⑦ By pressing the CLEAR key without having input a number, the unit returns to Step ② without doing anything else. Each press of this key after a number has been input deletes one digit.

```
[Player's ID Number Setting]
 ID Number ?
    0 0 0 0 0 0 0 0 1
 Compare
⑥ > * * * * * * * * *


 Input ID Number !
```

⑧ After entering all 9 digits, if you press the PLAY key, the unit compares the numbers input in Steps ② and ⑥, and only if the numbers match, that number is set as the ID. Then the unit automatically enters ID DATA Input Mode. If the numbers do not match, the disc tray is opened, and the unit exits ID Number Input Mode.

Note: If you press the PLAY button before inputting a 9-digit ID number, the unit returns to Step ⑥ without doing anything else.

```
[Player's ID Number Setting]
 ID Number ?
    0 0 0 0 0 0 0 0 1
 Compare
  > 0 0 0 0 0 0 0 0 1 OK?

⑧ <PLAY>  Enter

 Input ID Number !
```

ID Number Confirmation Mode

① To enter ID Number Confirmation Mode after the ID number and the ID data are set, press the ESC key then the STEREO key.

② The ID number already set is displayed.
(It is also displayed on the FL display.)

③ Enter a 9-digit number for comparison. This is not required when you only wish to check the ID number visually.
(The number is also displayed on the FL display.)

④ By pressing the CLEAR key without having input a number, you can exit this mode. Each press of this key after a number has been input deletes one digit.



⑤ After entering all 9 digits, if you press the PLAY key, the unit compares the number entered in Step ② with the ID number set, and only if the numbers match, the unit automatically exits ID Number Confirmation Mode. If an ID data has not been entered, the unit enters ID DATA Input Mode. If the numbers do not match, the disc tray is opened, and the unit exits ID Number Confirmation Mode.

Note: If you press the PLAY button before inputting a 9-digit ID number, the unit returns to Step ④ without doing anything else.

⑥ After entering all 9 digits, if you press the STOP key, the unit compares the number entered in Step ③ with the ID number set, and only if the numbers match, the unit automatically deletes the ID number and exits this mode. If the numbers do not match, the disc tray is opened, and the unit exits this mode. (The STOP key is not accepted after all 9 digits have been entered.)



• Indication of an ID number already set

An ID number already set is displayed in the following cases:

1) When the ESC key then the CLEAR key are pressed, user settings are cleared, then the ID number set is displayed on the screen. In this case, the ID number is not displayed on the FL display.
2) When the unit enters ID Number Confirmation Mode by your pressing the ESC key then the CLEAR key, the ID number set is displayed. In this case, the ID number is also displayed on the FL display.
   If you only need to confirm the ID number, you can exit this mode by pressing the CLEAR key or turning off the power.

• Indication when no ID number is set

If no ID number is set, the message "No ID Number!" flashes on the screen and FL display for a few seconds after the power is turned on or during Stop mode.

ID DATA Input Mode

① To enter ID DATA Input Mode, with the ID number set, press the ESC key then the STEREO key.

② When the STEREO key is pressed, the unit enters ID DATA Input Mode.



③ If the DVD DATA DISC (GGV1133) is loaded in this mode, the unit automatically starts reading the data.
(If the DVD DATA DISC has already been loaded, the unit does not start reading the data. In this case, open then close the tray.)

④ To exit this mode, press the CLEAR key. While data are being read from the DVD DATA DISC (GGV1133), you cannot exit this mode.



⑤ When writing of the data read from the disc to flash ROM is completed, "Rom Write OK!" is displayed. After seeing this message, you can exit this mode by pressing the CLEAR key.

Note: Whether or not the data have been written to flash ROM can be confirmed by watching for the message "Rom Write OK!" being displayed after the disc is read.



⑥ If the data cannot be read from the disc, "Disc Error!" is displayed on the screen, and the disc is ejected.



• Indication when the data have not been set
If no ID data are set after the ID number is changed, the message "NO ID DATA" flashes on the screen and FL display for a few seconds after the power is turned on or during Stop mode.

7.1.8 TROUBLE SHOOTING

Check the error history first. (See "7.1.6 MECHANICAL ERROR HISTORY")
When the error history is not displayed, see the below table.

No.	Symptoms	Diagnosis Contents	Possible Defective Points
1	The power is not turned on.	Check the voltage of EV+3.3V, –28V and FLDC on the POWER SUPPLY Unit.	**POWER SUPPLY Unit**
		Are wires of output connector (POWER SUPPLY Unit) and CN401 (DVDM Assy) disconnected or damaged ?	Connector / cable
		Check that the voltage at IC101-pin 22 (KEY0) on the FLKY Assy becomes 0 V when the POWER key is pressed and 3.3 V when it is released.	**FLKY Assy** Tact SW (when operation of only the POWER key on the main unit is not accepted)
		Check that the voltage at IC101-pin 17 (SEL IR) on the FLKY Assy is in the range between 0 and 3.3 V while receiving signals from the remote control unit when any key on it is pressed.	**FLKY Assy** Remote receiver section (when operation of only the POWER key on the remote control unit is not accepted)
2	An opening screen is not displayed on the monitor (The FL display lights. The mechanism does not work.)	Is the level at both IC101-pin 12 (XRESET) and pin 11 (POWER ON) on the FLKY Assy "H" ?	**FLKY Assy** FL Control IC (IC101)
		• Check the voltage of E+6V and SW+1.8V on the POWER SUPPLY Unit. • Check the voltage of P-CONT is about 3V on the POWER SUPPLY Unit.	**POWER SUPPLY Unit**
		Check that the following voltage are output : IC401-pin 1 : 5V, IC402-pin 3 : 3.3V, IC403-pin 5 : 3.3V on the DVDM Assy.	**DVDM Assy** 5V Regulator IC (IC401) 3.3V Regulator IC (IC402) 3.3V Regulator IC (IC403)
		Are resonators (X6401 : 27MHz, X301 : 20MHz) on the DVDM Assy oscillating ?	**DVDM Assy** Crystal resonator (X6401 and X301)
		Refer to contents of an FE error displayed on the FL display. (I2C communication line defectiveness, etc.)	**DVDM Assy** Front End IC (IC301)
		• Is a signal input into IC603-pin26 (CE_FLASH) on the DVDM Assy ? (Is a signal fluctuating for several seconds after the power is turned on ?) → Communication with flash ROM. • Are the signals input into IC602-pin 16 (SMIWE), pin 19 (SMICS0) and pin 38 (SMICLK) on the DVDM Assy ? (Is a signal fluctuating ?) → Communication with SDRAM	**DVDM Assy** Back End IC (IC601) Flash ROM (IC603) SDRAM (IC602)
		Is a signal output from IC603-pin 28 (CPU_OE) on the DVDM Assy? (Is a signal fluctuating for several seconds after the power is turned on ?)	**DVDM Assy** Flash ROM (IC603)
		Is a signal input into IC101-pin 16 (FP_ACK) on the FLKY Assy ? (Is a signal fluctuating ?) → Communication with FL Control IC	**DVDM Assy** Back End IC (IC601) **FLKY Assy** FL Control IC (IC101)
		Is a signal output from IC101-pin 10 (XRDY) on the FLKY Assy ? (Is a signal fluctuating in the range of 0-3V ?)	**FLKY Assy** FL Control IC (IC101)
		Are the signals output from IC101-pin 9, pin 8 and pin 7 on the FLKY Assy ? (in the range of 0-3V)	**DVDM Assy** Back End IC (IC601) – **FLKY Assy** FL Control IC (IC101) communication line
3	An opening screen is not displayed on the monitor (The FL display lights. The mechanism does not work.)	Check the video signal path between Back End IC (DVDM Assy IC601) and video-out terminal (see the block diagram)	**DVDM Assy, JCKB Assy** Video circuit after Back End IC (IC601)

No.	Symptoms	Diagnosis Contents	Possible Defective Points
4	A tray cannot be opened. (An opening screen is displayed on the monitor)	Does the voltage of CN103-pin 3 and pin 5 on the DVDM Assy change normally ? Pin 3 (XCLOSE): Tray is fully closed: "H" Pin 5 (OPEN): Tray is fully opened: "H"	**DVDM Assy** Front End IC (IC301) Tray SW
		Is a LOAD-DRV signal reaching ?	**DVDM Assy** Back End IC (IC601)
		Are the signals output from IC101 pin 36 and pin 37 (CN103 pin 1 and pin 2) on the DVDM Assy ? Pin 36: Approx. 6V during opening tray approx. 0V during closing tray. Pin 37: Approx. 0V during opening tray approx. 6V during closing tray.	**DVDM Assy** FTS Driver IC (IC101)
		Are wires of CN104 and CN103 on the DVDM Assy disconnected or damaged ?	Connector / cable
		Does the voltage of CN102-pin 12 change by pressing the Inside switch.	Inside switch
5	Playback impossible (no focusing)	Are the signals output from IC101-pin 34 (F_DRV) and pin 35 (F_RTN) on the DVDM Assy ?	**DVDM Assy** FTS Driver IC (IC101)
		Does 650-nm LD emit light ? Does a pickup lens move up / down ? Does an actuator spring bend ?	Pickup
		Are plastic parts damaged ? Or is a shaft detached ? Is the turntable detached or tilted ?	Mechanism section (motor)
		Is flexible cable of CN101 on the DVDM Assy disconnected or damaged ?	Flexible cable / connector
		Is signal output from IC301-pin 33 (FACT) on the DVDM Assy ? (Device control of about 500 mV is output usually. It is fluctuated by about ± 100 mV with focus up / down.)	**DVDM Assy** Front End IC (IC301)
6	Playback impossible (Spindle does not turn)	Are the signals output from IC101-pin 12 (A3), pin 13 (A2) and pin 14 (A1) on the DVDM Assy ? Is pin 41 (PS) fixed LOW and is pin 38 (SB) fixed HIGH ?	**DVDM Assy** FTS Driver IC (IC101)
		Is there any part detached from the spindle motor ? Or Is there any foreign object lodged in it ?	Mechanism section (Spindle motor)
		Are wires of CN102 on the DVDM Assy disconnected or damaged ?	Flexible cable / connector
		Is signal output from IC301-pin 44 (SPDL_PDM) on the DVDM Assy ?	**DVDM Assy** Front End IC (IC301)
7	Playback impossible (Playback stops)	Does 650-nm LD deteriorate ? If the voltage at both ends of R201 on the DVDM Assy is 0.7 V or more, the 650-nm LD is definitely deteriorated.	650-nm LD deteriorated. (When playback of a DVD is impossible)
		Does 780-nm LD deteriorate ? If the voltage at both ends of R211 on the DVDM Assy is 1.2 V or more, the 780-nm LD is definitely deteriorated.	780-nm LD deteriorated. (When playback of a CD is impossible)
		Is there abnormality in FG waveform ?	**DVDM Assy** FG output : FTS Driver IC (IC101)
		Are there scratches or dirt on the disc ?	Disc
8	Picture disturbance during playback (block noise, freeze, other)	Are there scratches or dirt on the disc ? Is there a problem with the format of the disc ?	Disc
9	No sound (Picture is normal)	Check the waveform (BCK, LRCK, MCLK, DATA).	**DVDM Assy** Back End IC (IC601)
		Is signal output from signal (Main ch: IC201-pin 17, pin 18, pin 13, pin 12 / Multi ch: IC301, IC401-pin 9, pin 10) on the JCKB Assy ?	**JCKB Assy** Audio Dac IC (IC201) Audio Dac IC (IC301, IC401)

7.1.9 SEQUENCE AFTER POWER ON

Flow chart from power on to the picture output



7.1.10 DISASSEMBLY

Note: For performing the diagnosis shown below, the following jig cables for service are required:
• GGD1330 ×2

Diagnosis of the PCBs

Procedures ; JCKB Assy : 1 → 2 → 3
DVDM Assy : 1 → 2 → 4

1 Bonnet and Tray Panel

① Remove the Bonnet by removing the five screws.
② Press the ⏻ STANDBY/ON button to turn on the power.
③ Press the ⏏ button to open the tray.
④ Remove the tray panel.
⑤ Press the ⏏ button to close the tray.
⑥ Press the ⏻ STANDBY/ON button to turn off the power.



How to open the Tray when the power cannot be on

Insert a screwdriver (small) into the slit located at the bottom of the unit, and slide the projection of the drive gear in the loading mecha. assy in the direction of the arrow, as indicated in the photo. If the tray pops out a little, fully pull it out by a hand.



2 Front Panel Section

① Remove the six hooks.
② Remove the front panel section.



3 JCKB Assy

① Remove the rear panel by removing the nine screws. (Remove the ten scews for LFXJ type.)



② Remove the five screws.



③ Remove the JCKB Assy and stand it against the other parts.

Diagnosis



4 DVDM Assy

① Exchange the two flexible cables for the two jig cables.

② Remove the three screws.



③ Remove the DVDM Assy and stand it against the other parts.

Diagnosis



Removing the Traverse Mecha. Assy-S and Pickup Assy-S

1 Loading Mecha. Assy

① Remove the bridge by removing the one screw.

② Pull out the tray, then remove it by pressing the hook.

③ Short-circuit two points of C and D by soldering.

Note: After replacement, connect the flexible cable, then remove the soldered joint (open).

④ Remove the four connectors from the Loading Mecha. Assy.

⑤ Remove the four screws that secure the Loading Mecha. Assy to the unit.



Note when reinserting the Tray

When reinserting the Tray, first align the triangle printed on the Loading Base and the pin of the Drive Cam, then insert the Tray.



2 Traverse Mecha. Assy-S

① Dislodge the flexible cables from their factory placement.



● Bottom View

② Remove the four hooks.

③ Remove the Traverse Mecha. Assy-S.



3 Pickup Assy-S

Note: The Pickup Assy-S can be removed without removing the Traverse Mecha. Assy-S. (shown as Step 2.)

① Dislodge the flexible cable for the pickup from its packaged placement.

② Remove the flexible cable for the pickup.



● Bottom View

③ Remove the two adjustment screws and two adjustment springs.

④ Remove the Pickup Assy-S.



⑤ Remove the two screws.

Note: The screws are secured with epoxy. Make sure to apply epoxy after reattaching the screws.



Arrangement of the flexible cable for the spindle motor

: Conductive surface



● Bottom View

Arrangement of the flexible cable for the stepping motor

: Conductive surface



● Bottom View

Arrangement of the flexible cable for the pickup

: Conductive surface

Note:
Be sure to move the Pickup Assy-S to the innermost perimeter.

① Fold the flexible cable inward at the position of the reference line.

② Attach the flexible cable of the pickup to the connector.

③ Fold the flexible cable of the pickup with the backing inward.



④ Pass the flexible cable through the hook not allowing any slack.



⑤ Fold the flexible cable as indicated in the photo.

⑥ Hook the part folded in Step ① to the hook.



⑦ Pass the flexible cable below the hook, and fold it back.



⑧ Fold the flexible cable back at the hook.



⑨ Fold the flexible cable along the hook.



7.2 IC

• The information shown in the list is basic information and may not correspond exactly to that shown in the schematic diagrams.

• List of IC

STM6316ATXXA, STI5588CVB, SAA7893HL/C2, M63108FP, PE5374A

■ STM6316ATXXA (DVDM ASSY : IC301)

• FRONT END IC

● Block Diagram



● Pin Function

No.	PIN name	description	detail
1	IREF	12.7kF	Analog block reference part
2	GNDAI	GNDA	analog gnd
3	RFIN	capacitor	RF signal C association input to a demodulation block
4	RFOUT	capacitor	B1+B2+B3+B4 mixture listing from an analog block
5	VCCA18	1V8A	analog 1V8
6	A	B1	PU - B1 input
7	GNDMN	GNDA	analog gnd
8	B	B2	PU - B2 input
9	VCC33MN	3V3A	analog 3V3
10	REFD	to pick up	2V1 output for PU
11	VCC18MN	1V8A	analog 1V8
12	D	B4	PU - B4 input
13	VCCA18IS	1V8A	analog 1V8
14	C	B3	PU - B3 input
15	VCCA33IS	3V3A	analog 3V3
16	GNDAIS	GNDA	analog gnd
17	VCC33SD	3V3A	analog 3V3
18	VCC18SD	1V8A	analog 1V8
19	GNDSD	GNDA	analog gnd
20	F	C	PU-3 beam C input
21	E	A	PU-3 beam A input
22	VSHIELDIS	GNDA	analog gnd
23	VCC18ADC	1V8A	analog 1V8
24	GNDADC	GNDA	analog gnd
25	VSHIELDADC	GNDA	analog gnd
26	VCC33DAC	3V3A	analog 3V3
27	GNDDAC	GNDA	analog gnd
28	SPINDLE	560ohm(st2)	DAC current listing for stepper drive
29	SLEDGE	560ohm(st1)	DAC current listing for stepper drive
30	REFEXT	20K1%	Reference for DAC
31	REFGND	refext	analog gnd
32	REFDAC	560ohm1%	DAC reference
33	FACT	560ohm1%	DAC current listing for focus
34	TACT	560ohm1%	DAC current listing for tracking
35	VCC18DAC	1V8A	analog 1V8
36	PC0	FG	FG pulse input
37	PC1	PS	Driver control signal
38	PC2	tray SW1(open)	SW input for tray OPEN position
39	PC3	SB	Driver control signal
40	PC4	SLD position	Inside SW input

No.	PIN name	description	detail
41	VSS	GNDD	digital gnd
42	VDD33	3V3D	digital 3V3
43	PC5	780/X650	780nm/650nmLD change control signal
44	PC6	spinde PDM	Control PDM listing for spindle drive
45	PC7	opicgain	OEIC gain control signal
46	PD7	03PU/X02PU	Pull-up settlement
47	VSS	GNDD	digital gnd
48	VDD18	1V8D	digital 1V8
49	PD6	(debug)	test
50	PD5	(debug)	test
51	PD4	(DSPclk)	test
52	PD3	(DSPdata)	test
53	PD2	(DSPstrb1)	test
54	PD1	error monitor	Terminal for TRKG error monitor (30KHzLPF add need)
55	PD0	tray PDM drive	Control PDM signal for tray drive
56	VSS	GNDD	digital gnd
57	VDD33	3V3D	digital 3V3
58	OUT_ERR	RS_ERROR	BE DATA I/F
59	OUT_EVALID	RS_ERR_EN	BE DATA I/F
60	VSS	GNDD	digital gnd
61	OUT_CLK	RS_BCLK	BE DATA I/F
62	VDD18	1V8D	digital 1V8
63	OUT_DVALID	RS_DVALID	BE DATA I/F
64	OUT_DATA	RS_DATA	BE DATA I/F
65	OUT_SYNC	RS_ECCBST	BE DATA I/F
66	PE5	SCL(DMA)	FE routine download input
67	PE4	SDA(DMA)	FE routine download input
68	PE3	SCL	BE command I/F
69	PE2	SDA	BE command I/F
70	PE1	tray SW2(close)	SW input for tray CLOSE position
71	PE0	DXXINT	FE status propagation signal
72	VSS	GNDD	digital gnd
73	VDD33	3V3D	digital 3V3
74	PF1	10K-pullup	Built-in facility setting terminal
75	PF0	10K-pulldown	Built-in facility setting terminal
76	VSS	GNDD	digital gnd
77	VDD18	1V8D	digital 1V8
78	PG1	to EMULATOR	Built-in facility setting terminal
79	PG0	to EMULATOR	Built-in facility setting terminal
80	TEST	10K-pulldown	test

No.	PIN name	description	detail
81	RESET_N	RESET	RESET input
82	VSSADC	GNDA	analog gnd
83	VDD18ADC	1V8A	analog 1V8
84	GNDPLL	GNDA	analog gnd
85	PLLOFF	GNDA	analog gnd
86	FREOUT	20MXtal	SYSTEMCLK oscillating circuit
87	FREIN	20MXtal	SYSTEMCLK oscillating circuit
88	VCC18PLL	1V8A	analog 1V8
89	LD1	650nmLD	650nmLD driving signal
90	LD2	780nmLD	780nmLD driving signal
91	VCCA33	3V3A	digital 3V3
92	TWSEL	CD_VR/GND	Monitor diodes VR junction terminal for CD
93	LMD1	LMD/LMD1	Monitor voltage junction terminal
94	LMD2	DVD_VR/LMD2	Monitor diodes VR junction terminal for DVD
95	GNDL	GNDA	analog gnd
96	TST_PM	nc	test
97	TST_SLICE	nc	test
98	TST_ADC	nc	test
99	RFSACD	SACD_IC	RF signal output
100	VBGFILT	capacitor	Condenser junction terminal for inside reference stability

■ STI5588CVB (DVDM ASSY : IC601)

• BACK END IC

● Pin Configuration



● Block Diagram



● Pin Function

No.	Pin Name	Dir.	Pin Function
1	FP_SO	OUT	Front Panel / DAC interface. Serial transfer data output.
2	A_DATA3	OUT	Data output to SACD decoder
3	VCLK	OUT	reserved
4	VDD_3V3	-	3.3 V Power supply
5	VSS	-	Ground
6	B_DATA	OUT	SACD data output to SACD decoder
7	B_BCLK	OUT	SACD bit clock output to SACD decoder
8	B_FLAG	OUT	SACD flag output to SACD decoder
9	TRYPOS	OUT	It is not connected except 5 Disc Changer.
		IN	Only 5 Disc Changer. Tray rotation pulse input. CAPTURE_IN0 can be used.
10	SQUEEZE	OUT	Output signal for S-Video output S1/S2 control. 'H' : squeeze output mode.
11	RTS	OUT	UART(RS-232C) Request To Send signal output.
12	LETTER	OUT	Output signal for S-Video output S1/S2 control & EURO(SCART) connector (FUNCTION SWITCHING) signal. 'H' : letter-box output mode.
13	CTS	IN	UART(RS-232C) Clear To Send signal input.
14	VDD_1V8	-	1.8 V Power supply
15	VSS	-	Ground
16	FE_DATA	IN	Front-End L6316 stream interface. Serial data input.
17	FE_BCLK	IN	Front-End L6316 stream interface. Serial clock input.
18	FE_DVALID	IN	Front-End L6316 stream interface. Data valid flag input.
19	FE_SYNC	IN	Front-End L6316 stream interface. Serial synchronize flag input.
20	FE_EVALID	IN	Front-End L6316 stream interface. Error valid flag for RS_split.
21	FE_ECCBST	IN	Front-End L6316 stream interface. ECC block start flag for RS_split.
22	I/XP	OUT	Output signal for a change of interlace/Progressive output for video driver. 'L' : progressive 'H' : interlace
23	VDD_RGB	-	RGB circuit 3.3 V Power supply
24	VSS_RGB	-	RGB circuit Ground
25	B_OUT	OUT	B / Cb
26	G_OUT	OUT	G / Y
27	R_OUT	OUT	R / Cr
28	VREF_RGB	IN	RGB DAC reference
29	IREF_RGB	IN	RGB DAC current reference
30	VDD_YCC	-	YC circuit 3.3 V Power supply
31	VSS_YCC	-	YC circuit Ground
32	Y_OUT	OUT	Y
33	C_OUT	OUT	C
34	CV_OUT	OUT	CV
35	VREF_YCC	IN	YCC DAC reference
36	IREF_YCC	IN	YCC DAC current reference
37	VDD_1V8	-	1.8 V Power supply
38	VSS	-	Ground

No.	Pin Name	Dir.	Pin Function
39	FE_XDRV_MUTE	OUT	It is not connected except 5 Disc Changer.
			Only 5 Disc Changer. Output signal for motor driver muting. 'L' : muting
40	FE_OPEN	OUT	It is not connected except 5 Disc Changer.
		IN	Only 5 Disc Changer. Input signal for tray position. 'H' : complete OPEN position.
41	FE_CLOSE	OUT	It is not connected except 5 Disc Changer.
		IN	Only 5 Disc Changer. Input signal for tray position. 'H' : complete CLOSE position.
42	CLAMP	OUT	It is not connected except 5 Disc Changer.
		IN	Only 5 Disc Changer. Input signal for showing disc clamp position. 'H' : complete disc clamp position.
43	XUNCLAMP	OUT	It is not connected except 5 Disc Changer.
		IN	Only 5 Disc Changer. Input signal for showing disc un-clamp position. 'H' : complete disc clamp position.
44	DISC_SNS	OUT	It is not connected except 5 Disc Changer.
		IN	Only 5 Disc Changer. Input signal for disc existing. 'L' : existing
45	XDRVMUTE2	OUT	reserved
46	TP-x	OUT	reserved
47	VDD_3V3	-	3.3 V Power supply
48	VDD_PCM	-	1.8 V Power supply
49	VSS_PCM	-	Ground
50	VSS	-	Ground
51	A_BCK	OUT	Audio DAC clock
52	A_DATA0	OUT	Audio DAC Front L,R data
53	A_DATA1	OUT	Audio DAC Center, LFE data
54	A_DATA2	OUT	Audio DAC Surround L, R data
55	A_MCLK	OUT	Audio DAC Master clock
56	A_LRCK	OUT	Audio DAC L/R clock
57	A_DOUT	OUT	S/PDIF(IEC60958) digital audio output.
58	SMI_A4	OUT	SMI SDRAM Address
59	SMI_A5		
60	SMI_A6		
61	SMI_A7		
62	SMI_A8		
63	SMI_A9		
64	VDD_1V8	-	1.8 V Power supply
65	VSS	-	Ground
66	SMI_A3	OUT	SMI SDRAM Address
67	SMI_A2		
68	SMI_A1		
69	SMI_A0		
70	SMI_A10		
71	SMI_A11		
72	SMI_A12		
73	SMI_A13		

No.	Pin Name	Dir.	Pin Function
74	SMI_CS0	OUT	SMI SDRAM chip select 'L'.
75	SMI_CS1	OUT	reserved
76	SMI_RAS	OUT	SMI SDRAM RAS 'L'
77	SMI_CAS	OUT	SMI SDRAM CAS 'L'
78	SMI_WE	OUT	SMI SDRAM Write Enable 'L'
79	SMI_DQML	OUT	SMI SDRAM Lower DQM 'L': Lower select
80	SMI_DQMU	OUT	SMI SDRAM Upper DQM 'L': Upper select
81	VDD_3V3	-	3.3 V Power supply
82	SMI_CLKIN	IN	External SDRAM clock input.
83	VSS	-	Ground
84	SMI_D0	I/O	SMI SDRAM Data
85	SMI_D1		
86	SMI_D2		
87	SMI_D3		
88	SMI_D4		
89	SMI_D5		
90	SMI_D6		
91	SMI_D7		
92	SMI_D8		
93	SMI_D9		
94	VDD_1V8	-	1.8 V Power supply
95	SMI_CLKOUT	OUT	SDRAM clock output.
96	VSS	-	Ground
97	SMI_D10	I/O	SMI SDRAM Data
98	SMI_D11		
99	SMI_D12		
100	SMI_D13		
101	SMI_D14		
102	SMI_D15		
103	TRACK_CROSS	OUT	reserved
104	DSD_XPCM	OUT	reserved
105	DAC_XRST	OUT	Reset signal of audio DAC. 'L': Reset
106	ADC_PCMCLK	OUT	reserved
107	VDD_3V3	-	3.3 V Power supply
108	VSS	-	Ground
109	XTRST	IN	Diagnostic Control Unit interface
110	TMS	IN	Diagnostic Control Unit interface
111	TDO	OUT	Diagnostic Control Unit interface
112	TDI	IN	Diagnostic Control Unit interface
113	TCK	IN	Diagnostic Control Unit interface
114	ROTDRV	OUT	Only 5 disc changer. PWM output for tray rotation.
115	BOOT_FROM_ROM	IN	Boot select 'L' : Boot from DCU. 'H' : Boot form ROM.
116	LOAD_DRV	OUT	Only 5 disc changer. PWM output for tray Open/Close drive.
117	CPU_OE	OUT	OE signal for 16M bits FLASH memory for firmware. 'L': enable

No.	Pin Name	Dir.	Pin Function
118	CPU_SDCK	OUT	CLOCK for 64M bits SDRAM for debugging firmware.
119	VDD_1V8	-	1.8 V Power supply
120	PIXCLK	IN	Master 27MHz system clock input.
121	VSS	-	Ground
122	VDD_PLL	-	Clock PLL circuit 1.8 V Power supply
123	VSS_PLL	-	Clock PLL circuit Ground
124	XRESET	IN	Power ON system RESET signal. 'L': reset
125	SACD_IRQ	IN	Interrupt signal from SACD decoder
126	FP_XRDY	IN	Front Panel interface. Hand-shake input.
127	FE_INT	IN	Interrupt input signal from Front-End L6316.
128	F_XWE, SD_DQML	OUT	Flash memory write enable. Debug SDRAM/SRAM Lower DQM. 'L': enable, Lower select.
129	SD_DQMU	OUT	Debug SDRAM/SRAM Upper DQM 'L':upper select
130	SD_RXW	OUT	Debug SDRAM Read/Write 'L':write, 'H':read
131	CPU_WAIT	IN	CPU wait 'H' input
132	CE_FLASH	OUT	Flash memory Chip Enable 'L'.
133	CE_SACD	OUT	Licence signal from SACD decoder
134	CPU_CE1	OUT	reserved
135	SD_XRAS	OUT	Debug SDRAM RAS 'L' Debug SRAM chip enable 'L'
136	VDD_3V3	-	3.3 V Power supply
137	VSS	-	Ground
138	CPU_RAS1	OUT	reserved
139	SD_XCAS	OUT	Debug SDRAM CAS 'L'
140	SD_XCS	OUT	Debug SDRAM Chip Select 'L'
141	CPU_D0	I/O	FLASH, Debug SDRAM/SRAM data
142	CPU_D1		
143	CPU_D2		
144	CPU_D3		
145	CPU_D4		
146	CPU_D5		
147	CPU_D6		
148	CPU_D7		
149	VDD_1V8	-	1.8 V Power supply
150	VSS	-	Ground
151	CPU_D8	I/O	FLASH, Debug SDRAM/SRAM data
152	CPU_D9		
153	CPU_D10		
154	CPU_D11		
155	CPU_D12		
156	CPU_D13		
157	CPU_D14		
158	CPU_D15		
159	VDD_3V3	-	3.3 V Power supply
160	VSS	-	Ground

No.	Pin Name	Dir.	Pin Function
161	CPU_A1	OUT	FLASH, Debug SDRAM/SRAM Address
162	CPU_A2		
163	CPU_A3		
164	CPU_A4		
165	CPU_A5		
166	CPU_A6		
167	CPU_A7		
168	CPU_A8		
169	CPU_A9		
170	CPU_A10		
171	VDD_1V8	-	1.8 V Power supply
172	VSS	-	Ground
173	CPU_A11	OUT	FLASH, Debug SDRAM/SRAM Address
174	CPU_A12		
175	CPU_A13		
176	CPU_A14		
177	CPU_A15		
178	CPU_A16		
179	CPU_A17		
180	CPU_A18		
181	CPU_A19		
182	CPU_A20		
183	CPU_A21		
184	VDD_3V3	-	3.3 V Power supply
185	VSS	-	Ground
186	XEXPE	OUT	reserved
187	FE_ERROR	IN	Front-End L6316 stream interface. ECC Error flag
188	VSEL1	OUT	EURO(SCART) connector (BLINKING) output signal 'L' : RGB output disable 'H' : RGB output enable
189	VSEL2	OUT	EURO(SCART) connector V/Y, R/C signal. 'L' : VRGB output = YCGB 'H' : VRGB output = VRGB
190	FE_RST	OUT	Front-End L6316. Hardware reset output. 'L' : reset
191	SACD_XRST	OUT	Reset signal of SACD decoder. 'L' : reset
192	XMMUTE	OUT	Output for tone quality enhancement
193	B_SYNC	OUT	Sector synchronization output to SACD decoder
194	SDA	I/O	Front-End L6316 command interface I2C bus serial data line.
195	SCL	OUT	Front-End L6316 command interface I2C bus serial clock line.
196	B_WCLK	OUT	Word clock output to SACD decoder
197	TXD	OUT	UART(RS-232C) data output
198	VDD_1V8		1.8 V Power supply
199	VSS	-	Ground
200	RXD	IN	UART(RS-232C) data input

No.	Pin Name	Dir.	Pin Function
201	XAMUTE	OUT	Output signal for analog audio output line muting. 'L' : muting
202	TRIGIN	IN	Diagnostic Control Unit interface
203	TRIGOUT	OUT	Diagnostic Control Unit interface
204	DAC_XCS0	OUT	Chip enable for audio DAC serial control. 'L' : enable
205	DAC_XCS1	OUT	Use of serial control of 5.1ch audio DAC is possible. 'L' : enable
206	FP_ACK	OUT	Front Panel / DAC interface. Hand-shake (acknowledge) output 'H'.
207	FP_SCK	OUT	Front Panel / DAC interface. Serial transfer clock output.
208	FP_SI	IN	Front Panel interface. Serial transfer data input.

■ M63018FP (DVDM ASSY : IC101)

• BTL Driver IC

● Pin Arrangement



● Block Diagram



● Pin Function

TERMINAL	SYMBOL	TERMINAL FUNCTION	TERMINAL	SYMBOL	TERMINAL FUNCTION
1	SL1IN	Slide control voltage input 1	42	OSC	PWM carrier oscillation set
2	SL2IN	Slide control voltage input 2	41	MU1	mute / brake select terminal 1
3	VM2	Motor Power Supply 2 (for Slide)	40	LOIN+	Loading control input(+)
4	RSL2	Slide current sense 2	39	VM3	Power Supply3 (for Loading)
5	SL2+	Slide non-inverted output 2	38	MU2	mute / brake select terminal 2
6	SL2-	Slide inverted output 2	37	LO-	Loading inverted output
7	GND	GND	36	LO+	Loading non-inverted output
8	RSL1	Slide current sense 1	35	FO-	Focus inverted output
9	SL1+	Slide non-inverted output 1	34	FO+	Focus non-inverted output
10	SL1-	Slide inverted output 1	33	GND	GND
11	GND	GND	32	VCC	Power Supply (for FS ,TS)
12	W	Motor drive output W	31	TO+	Tracking non-inverted output
13	V	Motor drive output V	30	TO-	Tracking inverted output
14	U	Motor drive output U	29	GND	GND
15	RSP	Spindle current sense	28	TOIN	Tracking control voltage input
16	HW-	HW- sensor amp. input	27	FOIN	Focus control voltage input
17	HW+	HW+ sensor amp. input	26	SPIN	Spindle control voltage input
18	HV-	HV- sensor amp. input	25	REF1	Reference voltage input 1 (for Spindle,Loading)
19	HV+	HV+ sensor amp. input	24	FG	Frequency generator output
20	HU-	HU- sensor amp. input	23	REF2	Reference voltage input 2 (for Slide,Focus,Tracking)
21	HU+	HU+ sensor amp. input	22	VM1	Motor Power Supply 1 (for Spindle)

■ PE5374A (FLKY ASSY : IC101)

• FL Control IC

● Pin Function

No.	Pin Name	I/O	Function
1	VDD1	–	Positive Power Supply (3.3 V)
2	VSS1	–	Ground Potential
3	X1	IN	Crystal Connection for Main System Clock Oscillation
4	X2	–	
5	IC	–	Internally Connected (Directly connect to VSS1)
6	RESET	IN	Reset Input
7	SCK1	IN	Serial Clock Input of Serial Interface
8	SI1	IN	Serial Data Input of Serial Interface
9	SO1	OUT	Serial Data Output of Serial Interface
10	XRDY	OUT	Hand-shake (Ready) Output of Serial Interface
11	POWER ON	OUT	Power Control Output
12	RESET OUT	OUT	System Reset Output
13	RESERVE OUT	OUT	Reserved (NC on this model)
14	NC	OUT	NC
15	HALT	IN	Halt Port "NC" : Use Halt Mode
16	ACK	IN	Hand-shake (Acknowledge) Input of Serial Interface
17	SEL IR	IN	Remote Control Input (Timer input of 8-bit remote control timer)
18	AVSS	–	Ground Potential for A/D Converter
19	NC	IN	8 digit model(DV-260,263) : Key3 Input (Analog input for A/D converter)
20	KEY2	IN	Key Input 2 (Analog input for A/D converter)
21	KEY1	IN	Key Input 1 (Analog input for A/D converter)
22	KEY0	IN	Key Input 0 (Analog input for A/D converter)
23	VSS0	–	Ground Potential to Ports
24	AVDD	–	Analog Power/Reference Voltage Input to A/D Converter (3.3 V)
25	VDD0	–	Positive Power Supply to Ports (3.3 V)
26	MS0_2	IN	Model (of player) Select (Set with a combinaition of this 3 ports)
27	MS0_1	IN	
28	MS0_0	IN	
29	MS1_2	IN	Destination (of player) Select (Set with a combinaition of this 3 ports)
30	MS1_1	IN	
31	MS1_0	IN	
32	TES	IN	H" : No System Reset mode , "L" : General mode
33	OEM	IN	H" : OEM Model , "L" : Pioneer Model
34	MIC IN	IN	Detection of Microphone "H" : Microphone connected
35	CHECKER	IN	H" : Checker Mode "L" : General Mode
36	ON POWER	IN	H" : Primary Power Switch Model , "L" : Secondary Power Switch Model
37	FL SET2	IN	FL-Controller Mode Select FL SET1 / 2 = "L" / "L" : 8 digit model
38	FL SET1	IN	
39	TEST2	OUT	(Test Port)
40	STAND BY LED	OUT	Stand By LED Port

No.	Pin Name	I/O	Function
41	LED5	OUT	LED Port 5
42	LED4	OUT	LED Port 4
43	LED3	OUT	LED Port 3
44	LED2	OUT	LED Port 2
45	LED1	OUT	LED Port 1
46	LED0	OUT	LED Port 0
47	TEST1	OUT	(Test Port)
48	TEST0	OUT	(Test Port)
49	NC	OUT	NC
50	NC	OUT	NC
51	P16	OUT	FIP Segment 17 Output
52	P15	OUT	FIP Segment 16 Output
53	NC	OUT	FIP Segment 15 Output
54	P14	OUT	FIP Segment 14 Output
55	P13	OUT	FIP Segment 13 Output
56	P12	OUT	FIP Segment 12 Output
57	P11	OUT	FIP Segment 11 Output
58	P10	OUT	FIP Segment 10 Output
59	VDD2	–	Positive Power Supply to FIP Controller/Driver (3.3 V)
60	VLOAD	–	Pull-down Resistor Connection of FIP Controller/Driver (-28V)
61	P9	OUT	FIP Segment 9 Output
62	P8	OUT	FIP Segment 8 Output
63	P7	OUT	FIP Segment 7 Output
64	P6	OUT	FIP Segment 6 Output
65	P5	OUT	FIP Segment 5 Output
66	P4	OUT	FIP Segment 4 Output
67	P3	OUT	FIP Segment 3 Output
68	P2	OUT	FIP Segment 2 Output
69	P1	OUT	FIP Segment 1 Output
70	NC	OUT	FIP Grid 11 Output
71	NC	OUT	FIP Grid 10 Output
72	NC	OUT	FIP Grid 9 Output
73	G8	OUT	FIP Grid 8 Output
74	G7	OUT	FIP Grid 7 Output
75	G6	OUT	FIP Grid 6 Output
76	G5	OUT	FIP Grid 5 Output
77	G4	OUT	FIP Grid 4 Output
78	G3	OUT	FIP Grid 3 Output
79	G2	OUT	FIP Grid 2 Output
80	G1	OUT	FIP Grid 1 Output

Disc / content format playback compatibility

General disc compatibility

This player was designed and engineered to be compatible with software bearing one or more of the following logos:

DVD-Audio DVD-Video DVD-R DVD-RW

Audio CD Video CD CD-R CD-RW

Super VCD Super Audio CD

Fujicolor CD

- KODAK Picture CD
- *is a trademark of Fuji Photo Film Co. Ltd.*

Other formats, including but not limited to the following, are not playable in this player:

DVD-RAM / DVD-ROM / CD-ROM*

* *Except those that contain MP3 or JPEG. See also "Compressed audio compatibility" and "JPEG file compatibility" below.*

DVD-R/RW and CD-R/RW discs (Audio CDs and Video CD/Super VCDs) recorded using a DVD recorder, CD recorder or personal computer may not be playable on this unit. This may be caused by a number of possibilities, including but not limited to: the type of disc used; the type of recording; damage, dirt or condensation on either the disc or the player's pick-up lens. See below for notes about particular software and formats.

CD-R/RW compatibility

- This unit will play CD-R and CD-RW discs recorded in CD Audio or Video CD/Super VCD format, or as a CD-ROM containing MP3 or JPEG files. However, any other content may cause the disc not to play, or create noise/distortion in the output.
- This unit cannot record CD-R or CD-RW discs.
- Unfinalized CD-R/RW discs recorded as CD Audio can be played, but the full Table of Contents (playing time, etc.) will not be displayed.

DVD-R/RW compatibility

- This unit will play DVD-R/RW discs recorded using the DVD-Video format that have been finalized using a DVD-recorder.
- This unit will play DVD-RW discs recorded using the Video Recording (VR) format.
- **DVD-RW** shows in the display when a VR format DVD-RW disc is loading.
- When playing a VR format DVD-RW discs that was edited on a DVD recorder, the screen may go momentarily black at edited points and/or you may see scenes from immediately before the edited point.
- This unit cannot record DVD-R/RW discs.
- Unfinalized DVD-R/RW discs cannot be played in this player.

PC-created disc compatibility

- If you record a disc using a personal computer, even if it is recorded in a "compatible format" as listed above, there will be cases in which the disc may not be playable in this machine due to the setting of the application software used to create the disc. In these particular instances, check with the software publisher for more detailed information.
- Check the DVD-R/RW or CD-R/RW software disc boxes for additional compatibility information.

Compressed audio compatibility

- This unit will play CD-ROM, CD-R, and CD-RW discs containing files saved in the MPEG-1 Audio Layer 3 (MP3) format with a sampling rate of 32, 44.1 or 48kHz. Incompatible files will not play and the message **Can't play this format** will be displayed (**NO PLAY** in the front panel display).
- Fixed bit-rate MP3 files are recommended. Variable bit-rate (VBR) MP3 files are playable, but playing time may not be shown correctly..
- The CD-ROM used to compile your MP3 files must be ISO 9660 Level 1 or 2 compliant. CD physical format: Mode1, Mode2 XA Form1. Romeo and Joliet file systems are both compatible with this player.
- Use CD-R or CD-RW media for recording your files. The disc must be finalized (i.e. the session must be closed) in order to play in this unit. This player is not compatible with multi-session discs. Only the first session of a multi-session disc will be recognized.
- This player only plays tracks that are named with the file extension .mp3 or .MP3.
- When naming MP3 files, add the corresponding file name extension (.mp3). Files are played according to the file extension. To prevent noise and malfunctions, do not use these extensions for other kinds of files.
- This player can recognize up to 999 files (MP3/JPEG) and up to 499 folders. If a disc exceeds these limits, only files and folders up to these limits will be playable. Files and folders are read/displayed in alphabetical order. Note that if the file structure is very complex, you may not be able to read/play all files on the disc.
- Folder and track names (excluding the file extension) are displayed.
- There are many different recording bit-rates available to encode MP3 files. This unit was designed to be compatible with all of them. Audio encoded at 128Kbps should sound close to regular CD Audio quality. This player will play lower bit-rate files, but please note that the sound quality becomes noticeably worse at lower bit-rates.

JPEG file compatibility

- Baseline JPEG and EXIF 2.1* still image files up to 8 mega-pixels are supported (maximum vertical and horizontal resolution is 5120 pixels). (**File format used by digital still cameras*)
- The CD-ROM used to compile your JPEG files must be ISO 9660 Level 1 or 2 compliant. CD physical format: Mode1, Mode2 XA Form1. Romeo and Joliet file systems are both compatible with this player.
- This player only displays files that are named with the file extension .jpg or .JPG.

7.4 CLEANING

Before shipping out the product, be sure to clean the following positions by using the prescribed cleaning tools:

Position to be cleaned	Cleaning tools
Pickup lenses	Cleaning liquid : GEM1004 Cleaning paper : GED-008

8. PANEL FACILITIES

Front panel



1 ⏻ STANDBY/ON
Press to switch the player on or into standby.

2 FL DIMMER
Press to dim or brighten the display.

3 Disc tray

4 ⏏ OPEN/CLOSE
Press to open or close the disc tray.

5 ⏸
Press to pause playback. Press again to restart.

6 ►
Press to start or resume playback.

7 TOP MENU
Press to display the top menu of a DVD disc.

8 ENTER & cursor buttons
Use to navigate on-screen displays and menus. Press **ENTER** to select an option or execute a command.

9 MENU
Press to display a DVD disc menu, or the Disc Navigator if a VR format DVD-RW, CD, Video CD/Super VCD, MP3 or JPEG disc is loaded.

10 RETURN
Press to return to a previous menu screen.

11 HOME MENU
Press to display (or exit).

12 ■
Press to stop the disc (you can resume play-back by pressing ► (play)).

13 Remote control sensor
The remote control has a range of up to about 7m (23ft).

14 Display

15 ⏮ ◄◄ and ►► ⏭
- Press and hold for fast reverse/forward scanning.
- Press to jump to the previous/next chapter or track.

16 RW COMPATIBLE
This mark indicates compatibility with DVD-RW discs recorded on a DVD recorder in Video Recording mode.

Rear panel connections



1 CONTROL IN / OUT
For passing remote control signals to other Pioneer components.

2 D1/D2 VIDEO OUT (LFXJ type only)
Use to connect this player to a TV with a D video input.

3 DIGITAL AUDIO OUT – COAXIAL
This is a digital audio output for connection to a PCM, Dolby Digital, DTS and/or MPEG-compatible AV receiver that has a coaxial digital input.

Connect using a commercially available coaxial digital audio cable.

4 COMPONENT VIDEO OUT
High quality video output for connection to a TV, monitor or AV receiver that has component video inputs.

Connect using a commercially available three-way component video cable. Be careful to match the colors of the jacks and cables for correct connection.

5 AUDIO OUT (2ch)
Two channel analog audio outputs for connection to your TV, AV receiver or stereo system.

Use the supplied audio/video cable when connecting these jacks. Match the colors of the jacks and cables for correct stereo sound.

6 AUDIO OUT (5.1ch)
Multichannel analog audio outputs for connection to an AV receiver with multi-channel inputs.

7 AC IN
Connect the supplied power cord here, then plug into a power outlet.

8 VIDEO OUT
Standard video output that you can connect to your TV or AV receiver using the supplied audio/video cable.

9 S (S-Video output)
S-Video output that you can use instead of the video output described in **8** above.

10 DIGITAL AUDIO OUT – OPTICAL
This is a digital audio output for connection to a PCM, Dolby Digital, DTS and/or MPEG compatible AV receiver that has an optical digital input. Connect using a commercially available optical digital audio cable.

Connect using a commercially available optical digital audio cable.

Display



1 V-PART
Lights when playing a video part of a DVD disc.

2 PRGSVE
Lights when the player is set to output progressive scan video.

3 GRP
Indicates that the character display is showing a DVD-Audio group number.

4 TITLE
Indicates that the character display is showing a DVD title number.

5 (●)
Lights when DV/SRS TruSurround is selected.

6 TRK
Indicates that the character display is showing a CD or Video CD/Super VCD track number.

7 CHP
Indicates that the character display is showing a DVD chapter number.

8 5.1CH
Lights when analog 5.1 channel output is selected.

9 D.MIX
During multichannel audio playback, indicates that the output signal has been "down-mixed" from the original audio source. This is an automatic function performed by the player in order to present the most appropriate audio mix to the speakers present in your system.

10
Lights in any of the repeat play modes.

11 REMAIN
Indicates that the character display is showing the disc or title/chapter/track remain time.

12 Character display

13
Lights during multi-angle scenes on a DVD disc.

14 II and ►
Indicates whether a disc is playing or paused.

15 DTS
Lights when a DTS soundtrack is playing.

16 D
Lights when a Dolby Digital soundtrack is playing.

Remote control



1 ⏻ STANDBY/ON
Press to switch the player on or into standby.

2 AUDIO
Press to select the audio channel or language.

3 SUBTITLE
Press to select a subtitle display.

4 Number buttons

5 TOP MENU
Press to display the top menu of a DVD disc.

6 ENTER & cursor buttons
Use to navigate on-screen displays and menus. Press **ENTER** to select an option or execute a command.

7 HOME MENU
Press to display (or exit) the on-screen display.

8 ◄◄ and ◄I/◄II
Use for reverse slow motion playback, frame reverse and reverse scanning.

9 ►
Press to start or resume playback.

10 I◄◄
Press to jump to the beginning of the current chapter or track, then to previous chapters/ tracks.

11 II
Press to pause playback; press again to restart.

12 PLAY MODE
Press to display the Play Mode menu. (You can also get to the Play Mode menu by pressing **HOME MENU** and selecting Play Mode).

13 SURROUND
Press to activate/switch off DDV/SRS TruSurround.

14 ▲ OPEN/CLOSE
Press to open or close the disc tray.

15 ANGLE
Press to change the camera angle during DVD multi-angle scene playback.

16 CLEAR
Press to clear a numeric entry.

17 ENTER
Use to select menu options, etc. (works exactly the same as the **ENTER** button in **6** above).

18 MENU
Press to display a DVD disc menu, or the Disc Navigator if a VR format DVD-RW, CD, Video CD/Super VCD, MP3 or JPEG disc is loaded.

19 RETURN
Press to return to a previous menu screen.

20 ►► and I►/II►
Use for forward slow motion playback, frame advance and forward scanning.

21 ►►I
Press to jump to the next chapter or track.

22 ■
Press to stop the disc (you can resume playback by pressing ► (play)).

23 DISPLAY
Press to display information about the disc playing.

24 ZOOM
Press to change the zoom level.